

XBO HPS for digital cinema projection

Xenon short-arc lamps


Areas of application

- Cinema projection




Product family features

- Short arc with highest luminance for brighter screen illumination
- A lifetime of reliable performances with constant 6000 K color temperature
- Easy to maintain
- High level of arc stability
- Hot restart and instant light on screen
- Dimmable in a wide range



Product family datasheet



Product line drawing

Product family datasheet

Technical data

Product description	Electrical data		Dimensions & weight			Temperatures & operating conditions	Lifespan	Additional product data
	Nominal current	Current control range	Length	Length with base excl. base pins/connection	Light center length (LCL)	Max. permitted ambient temp. pinch point	Lifespan	Base anode (standard designation)
XBO 2000 W/HPS L OFR	80.0 A	46...87 A	334.0 mm	297.00 mm	128.0 mm ¹⁾	230 °C	3000 h	SFaX30-14/68
XBO 3000 W/HPS OFR	105 A	60...112 A	334.0 mm	297.00 mm	128.0 mm ¹⁾	230 °C	1000 h	SFaX30-14/68
XBO 4200 W/HPS OFR	128 A	73...137 A	334.0 mm	297.00 mm	128.0 mm ¹⁾	230 °C	700 h	SFaX30-14/68
XBO 4200 W/HPS LL	128 A	69...131 A	334.0 mm	297.00 mm	128.0 mm ¹⁾	230 °C	1000 h	SFaX30-14/68

Product description	Base cathode (standard designation)	Capabilities
		Burning position
XBO 2000 W/HPS L OFR	SFc30-20/50	Other ²⁾
XBO 3000 W/HPS OFR	SFc30-20/50	Other ²⁾
XBO 4200 W/HPS OFR	SFc30-20/50	Other ²⁾
XBO 4200 W/HPS LL	SFc30-20/50	Other ²⁾

¹⁾ Distance from end of base to tip of electrode (cold)

²⁾ For vertical burning position: anode (+) on top

Product family datasheet

Safety advice

Because of their high luminance, UV radiation and internal pressure in both the hot and cold state, XBO lamps may only be operated in enclosed lamp casings specially constructed for the purpose. Xenon lamps are highly explosive. When hot, xenon lamps can cause burn marks. They should only be handled when the lamp is at room temperature. Always use the protective jackets supplied when handling these lamps. When packing the lamps and when installing or removing the lamps without their protective jackets, always wear protective clothing (face shield with neck protector, protective jacket and lint-free, cut-resistant gloves). For more information see the relevant in-pack leaflets and operating instructions.

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.