



## ChimeCom (C-123L) Series Door Answering and Audio Monitoring Sets



Residential and Commercial Applications

## Features and Benefits

### Replaces doorbell, easy to install

Reduce installation costs by using existing doorbell wire. No doorbell? *No problem!* The system only requires two wires, making installation a snap!

### DC powered or battery operated

Choose your preferred method to power the system: a 6V DC power supply or four C batteries.

### Pull cord included

Mount the master station in the exact location of an existing doorbell chime and use the pull cord to communicate.

### Door release

Push the door release button to conveniently unlock the entrance directly from the master station.

### Audio monitoring

Discreetly listen to activity at the door station with either the push of a button or the pull of a cord.

### Affordable system

Maintain your budget with this affordable, simple-to-use system.

### Reliable and designed to last

Install the system and have trouble-free use for years to come!



**Upgrade any doorbell to an Aiphone intercom for 2-way communication at the door!**

## Components

**Box Sets: select 1** (door station not sold separately—choose C-123L/A for a 1x1 system or C-123LW for a 1x2 system)



**C-123L/A**  
Single Master Station Box Set (includes one C-D door station and one C-ML/A master station)



**C-123LW**  
Dual Master Station Box Set (includes one C-D door station, two C-ML/A master stations, and one DAK-2S dual master station adaptor kit)

### Door Station, Master Station, and Adaptor Kit



**C-D**  
Audio Door Station (included with both C-123L/A and C-123LW box sets—not sold separately)

- Pull cord included
- Dual master adaptor kit included (DAK-2S)
- Plastic cover
- Surface mount

4-3/4" H  
3-7/16" W  
1-1/8" D



**C-ML/A\***  
Audio Master Station (one included with C-123L/A box set and two included with C-123LW box set)

- Pull cord included
- Dual master adaptor kit included (DAK-2S)
- Plastic cover
- Surface mount

7-1/2" H 5-1/8" W 1-3/4" D



**DAK-2S**  
Dual Master Adaptor Kit (required for two C-ML/As to be used in a system—included with C-ML/A and C-123LW)

**\*If the C-123L/A box set is selected, one C-ML/A can be purchased separately to have a second master station.**

### Power Supply

(not included with box sets—sold separately)



**SKK-620C**  
6V DC Power Supply (one required per C-ML/A)

or



Four C Batteries (four batteries required per C-ML/A—not available to purchase through Aiphone)

### Accessories



**KMB-45**  
45° Mullion Mounting Bracket for C-D



**EL-12S**  
Electric Door Strike for Wood Frames (requires PT-1210N)



**PT-1210NA**  
12V AC Transformer (required for EL-12S)

## Specifications

<b>Power Source</b>	6V DC—use SKK-620C or four C batteries
<b>Communication</b>	Push-to-talk (simplex)
<b>Door Release</b>	N/O dry contact, 50V AC, 1A
<b>Wire Type</b>	Door Station to Master Station: 2-cond., overall shield—use Aiphone #822202 or Aiphone #821802
<b>Distance</b>	Door Station to farthest Master Station: 245' (22AWG) 590' (18AWG)



**SECURITY  
COMMUNICATION  
SOLUTIONS**

[aiphone.com](http://aiphone.com)

**Customer Service  
and Technical Support**

**(800) 692-0200**

Headquarters – Redmond, WA

East Office – Cherry Hill, NJ

Canada Office – Laval, QC

WATCH | CONNECT | LIKE | FOLLOW



ChimeCom (C-123L)  
Series Brochure

© 2022 Aiphone Corp.  
Revised 08/2022.  
All rights reserved.  
Designed in the USA.

The information in this brochure is subject to change without notice.