



Installation Guide

Push Button LED Dimmer



Table of Contents

Section	page
1.0 Product Range	1
2.0 Description	1
3.0 Features	1
4.0 Normal Operation	1
5.0 Minimum Bright Level Setting.....	1
6.0 Electrical Specification	2
7.0 Load Compatibility	2
8.0 Installation	2
9.0 Wiring Diagram.....	2
10.0 Warranty Statement.....	2

1.0 Product Range

Product No.	Description
LED-L400DIM-P.	Push Button LED Dimmer, 400VA

2.0 Description

The LED Dimmer is a rotary controlled, modular dimmer mechanism rated at 400VA.

Up to six dimmer mechanisms can be installed in a plate!

Designed for LED lamps, the unit utilises powerful and sophisticated dimming technology to provide control.

The LED Dimmer also incorporates over-current and thermal fuse cutoff (non-recoverable) protection devices and is capable of withstanding persistent short circuit conditions.

3.0 Features

- Modular dimming mechanism.
- Two-wire phase control wall plate dimmer.
- Soft-start for lamp and driver life.
- Provide optimised dimming of LED based lamps and drivers.
- Compatibility with incandescent lamps, 240V halogen lamps, Low voltage halogen lamp with dimmable electronic transformer, etc
- Wall or architrave mounting options.
- Wide range of plate styles and colour variants available.
- Suitable for new installations or retro-fit applications.
- Inbuilt Over-Current and Over-Temperature protection.
- Full short circuit protection.
- Immune to high frequency (ripple) signal injection on mains supply.
- Complies with Australian and International EMC Standards.

4.0 Normal Operation

Operation of Dimmer Push Switch:

Long press dimming button to dimming

Short press dimming button to of/off

5.0 Minimum Bright Level Setting

How to set the Minimum bright level :



Power on for 10 seconds, short press 5x, then long press (hold for more than 3 seconds) 2x to reset the minimum level and led.

Each step must be performed within 15 seconds, if no, it will time out and auto exit program without save

6.0 Electrical Specification

Parameter	Value
Nominal Operating Voltage	220-240Vac ~
Nominal Operating Frequency	50Hz
Maximum Load	400VA @1 Gang Derate for multi-gang applications
Minimum Load	5VA
Dimming Technique	Trailing Edge Phase Control
Mounting Centres	84mm Australian Pattern Plate
Shipping Weight	25g Dimmer Mechanism Only
Safety Compliance	AS/NZS3100, AS/NZS3133, IEC60669-2-1
EMC Compliance	AS/NZS CISPR15, IEC60669-2-1 (26.1, 26.2), IEC61000-3-2 (Excepting when used in conjunction with Electronic loads)
Specifications Typical @ 240V ~ 25°C	
Suitable for Indoor Use Only	
No User Serviceable Parts Inside	

7.0 Load Compatibility

Load Symbol	Compatible Loads	Product Number
		LED-L400DIM-P.
	Dimmable LED Lighting	5-150W
	Incandescent Lighting 240V Halogen Lamps	10-400W



8.0 Installation

To connect the required lighting loads, then follow the following steps:

Leave the dimmer connected, but remove the dimming cap from the top button of the dimmer.



9.0 Wiring Diagram



NOTE:

- The LED dimmer series are designed for One-Way or Two-Way operation as above diagrams.
- Two or more dimmers cannot be connected in parallel or series to control the same load from two different locations.
- Dimmer Mechanism wiring is not polarity sensitive
It is illegal for persons other than an appropriately licensed electrical contractor or other persons authorised by legislation to work on the fixed wiring of any electrical installation. Penalties for conviction are severe!

10.0 Warranty Statement

1. This DimEzy product is guaranteed against faulty workmanship and materials for a period of two years from the date of installation.
2. This warranty is expressly subject to the DimEzy product being installed, wired, tested, operated and used in accordance with the manufacturer's instructions.