


LED WALL LIGHT

Product Manual



MODEL: BDB55-3 3-LBA55M

COMPONENTS AND STRUCTURE

BDB55-3



3-LBA55M



- 1. Cover
- 2. LED Light Source
- 3. Lamp Base

US 1.5m(4.92ft)
3x18AWG

PARTS LIST



A Machine Screw
QTY: 3



B Expansion Rubber Plug
QTY: 3

SPECIFICATIONS

LED WALL LAMP		
Model	BDB55-3	3-LBA55M
Input Voltage	100-120V ~ 60Hz	
Input Current	0.5A	0.52A
Rated Power	55W	60W
Luminous Flux	5500lm	6000lm
CCT	6500K	
CRI	≥80	
Power Factor	≥0.9	
L70B50 lifetime	30000hours L70B50 @ 25°	
Beam Angle	120°	
t _a	-20-40°C/-4°F-104°F	
Luminaire Location	SUITABLE FOR WET LOCATIONS	
DIMENSIONS		
Dimensions (LxHxW)	272x112x151mm / 10.71x4.41x5.94 in	274x127x145mm / 10.78x5x5.71 in
Weight	0.9 kg / 1.98 lb	0.85 kg / 1.87 lb
Note:	The testing standard of the product's luminous flux: Place the three/two lights on the same horizontal surface for testing, and the tested luminous flux is the accurate luminous flux.	

PREPARATION

Check all components for damage, do not use the product if it is damaged.

Estimated Assembly Time: 10-30 minutes


TOOLS REQUIRED (not included)



Flathead screwdriver



Screwdriver



Electric drill



Eye Protection



Pliers



Step Ladder

WARNING:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. RISK OF SHOCK - BEFORE BEGINNING INSTALLATION, TURN OFF ELECTRICITY AT THE CIRCUIT BREAKER BOX OR THE MAIN FUSE BOX.

PREPARATION

CAUTION:

PLEASE MAKE SURE YOUR WALL SWITCH AND POWER AT MAIN CIRCUIT BREAKER BOTH ARE OFF.


IF IN DOUBT ABOUT ELECTRICAL INSTALLATION, CONSULT A LICENSED ELECTRICIAN.

WARNING: INSTALLING THIS LIGHT IN AN UNGROUNDED ELECTRICAL SYSTEM MAY CAUSE THE METAL PARTS OF THE LIGHT TO CARRY CURRENT IF ANY WIRES OR WIRE CONNECTIONS ARE DAMAGED OR LOOSE. IN THIS CASE, ANYONE WHO TOUCHES THE LIGHT WILL RECEIVE AN ELECTRIC SHOCK, RESULTING IN INJURY OR DEATH.


BE CAREFUL NOT TO DAMAGE OR CUT THE WIRE INSULATION (COVERING) DURING INSTALLATION. DO NOT LET THE WIRES TOUCH ANY SHARP EDGES.

INSTALLATION STEPS

Step 1: According to the spacing (see the "A" part of the picture) of two screw bits on the LED Light base, drill two mounting holes and drive the expansion rubber plugs into them.




Step 2: Put the base onto the prepared mounting holes and then screw it on.




INSTALLATION STEPS

Step 3: Adjust the lamp directions as you like.



Step 4: Plug the light into the main socket.



FCC Warning:

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

HK JW Illumination Co., Limited
Unit 616, 6/F., Kam Teem Industrial Building,
135 Connaught Road West, Sai Wan Hong Kong

Manufacturer/Hersteller: MDH LIGHTING LTD
Suite 302, 292 Strovolos Avenue, 2048 Strovolos Nicosia,
Cyprus

UK Importer: MDH LIGHTING LTD
69 Aberdeen Avenue, Cambridge CB2 8DL,
United Kingdom

Made in China

✉ support@olafuslife.com 🌐 www.olafuslife.com