


# Olafus®



## PIR LED WALL LIGHTS WITH MOTION SENSOR


Product Manual

### MODEL:


□ 3-LBG55M □ 3-LBG80KB □ BDD100G-3 □ 3-LBG40L

## COMPONENTS AND STRUCTURE


3-LBG55M





3-LBG80KB



BDD100G-3




3-LBG40L



1. Cover
2. LED Light Source
3. Lamp Base

2

## PARTS LIST



## SPECIFICATIONS


LED WALL LAMP				
Model	3-LBG55M	3-LBG80KB	BDD100G-3	3-LBG40L
Input Voltage	100-120V ~ 60Hz			
Input Current	0.57A	0.83A	0.83A	0.35A
Rated Power	65W	100W	100W	40W
Luminous Flux	6500lm	9000lm	9000lm	4000lm
CCT	6500K			
CRI	≥80			
Power Factor	≥0.9			
L70B50 lifetime	30000hours L70B50 @ 25°			
Beam Angle	120°			
ta	-20-40°C/-4°F-104°F			
Luminaire Location	SUITABLE FOR WET LOCATIONS			

3

## SPECIFICATIONS

DIMENSIONS		
Model	3-LBG55M	3-LBG80KB
Dimensions (LxHxW)	274x174x142mm / 10.79x6.85x5.59in	364x159x116 mm / 14.33x6.22x4.57 in
Weight	0.94 kg / 2.07 lb	1.18 kg / 2.6 lb
Model	BDD100G-3	3-LBG40L
Dimensions (LxHxW)	400x182x120 mm / 15.75x7.16x4.72 in	279x136x124 mm / 10.98x5.35x4.88 in
Weight	0.98kg/2.16lb	0.78 kg/1.7 lb


**Note:**  
The testing standard of the product's luminous flux. Place the three/two lights on the same horizontal surface for testing, and the tested luminous flux is the accurate luminous flux.



4

## OPERATION INSTRUCTIONS


1. SENS adjustable: It can be adjusted according to using location; low sensitivity with 5m for detection distance; high sensitivity with 10m, it fits for large room.
2. Can identify day and night: The consumer can adjust work ambient light. It can work in the daytime and at night when it is adjusted on the "+" position (max). It can work in the ambient light less than 10LUX when it is adjusted on the "-" position (min).
3. Time-delay adjustment: It can be set according to the consumer's desire. The minimum time is 10sec~35sec. The maximum is 7min~2min. Time-delay is added continually: When it receives the second induction signals after the first induction, it will compute time once more on the rest of the first time-delay basic (set time).



5


## OPERATION INSTRUCTIONS

Detection Range: 180°




- NOTE:**
1. The PIR sensor shall always be tilted slightly downward.
  2. The orientation angle of the sensor shall be between 0-45°.

**RECOMMENDED INSTALLATION HEIGHT: 6.5-13.1 feet above the ground.**




When mounted 8ft above the ground and the sensor is oriented horizontally, the maximum sensing distance is about 72ft.



When mounted 8ft above the ground and the sensor is 45° down, the minimum sensing distance is about 19ft.

**Note:** The detection distance of the sensor is the farthest when the ambient temperature is 25°C. Any temperature fluctuations above or below 25°C will affect the detection distance. If the light continues to detect motion while it is on, it will remain on until the motion stops.

**The motion sensor is more sensitive to horizontal movement than vertical movement.**



6

## PREPARATION


### NOTE:

Before beginning assembly of product, make sure all parts are present. Compare parts with parts list. If any part is missing or damaged, do not attempt to assemble the product. Estimated Assembly Time: 30-60 minutes.

Recommended to be installed on the ground above 2.5m (8.2 ft) and no higher than 5 m (16.4 ft).

Product appearance may vary from image shown.

TOOLS REQUIRED (not included)



### WARNING:

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.**

### CAUTION:

**PLEASE MAKE SURE YOUR WALL SWITCH AND POWER AT MAIN CIRCUIT BREAKER BOTH ARE OFF.**

**IF IN DOUBT ABOUT ELECTRICAL INSTALLATION, CONSULT A LICENSED ELECTRICIAN.**

7

## PREPARATION

### RISK OF SHOCK:

**BEFORE BEGINNING INSTALLATION, TURN OFF ELECTRICITY AT THE CIRCUIT BREAKER BOX OR THE MAIN FUSE BOX.**

### NOTE:

**BE SURE TO USE WIRE NUTS/CONNECTORS RATED FOR THE CORRECT GAUGE AND NUMBER OF WIRES USED.**

**MAKE SURE THERE ARE NO EXPOSED WIRE BUNDLES OUTSIDE THE WIRE NUT/CONNECTOR (IF APPLICABLE).**

**BE CAREFUL NOT TO DAMAGE OR CUT THE WIRE INSULATION (COVERING) DURING INSTALLATION. DO NOT LET THE WIRES TOUCH ANY SHARP EDGES.**

### WARNING:




**DO NOT CONNECT THIS LIGHT FIXTURE TO AN UNGROUNDED ELECTRICAL SYSTEM. ATTACH GROUND FIXTURE WIRE TO EITHER GREEN GROUND SCREW ON MOUNTING PLATE OR THE GROUND WIRE IN THE OUTLET BOX.**

**INSTALLING THIS LIGHT IN AN UNGROUNDED ELECTRICAL SYSTEM MAY CAUSE THE METAL PARTS OF THE LIGHT TO CARRY CURRENT IF ANY WIRES OR WIRE CONNECTIONS ARE DAMAGED OR LOOSE. IN THIS CASE, ANYONE WHO TOUCHES THE LIGHT WILL RECEIVE AN ELECTRIC SHOCK, RESULTING IN INJURY OR DEATH.**



8

## INSTALLATION STEPS

FOR WET LOCATION, MAKE SURE FILL FULL THE GAP OF EVA GASKET AND MOUNTING SURFACE WITH SEALING COMPOUND OR SILICONE GLUE.



9



**Note:**  
The raised part (RA) of the metal plate must be engaged with the recessed part (RE) of the base, otherwise it cannot be installed.

10

## Troubleshooting

Malfunction	Cause	Remedy
LED senses a movement, the light does not light up	<ol style="list-style-type: none"> <li>1. The light is not energized</li> <li>2. Other surrounding light sources make the light misjudge it as daytime</li> <li>3. During the day, the brightness is in night mode</li> <li>4. Internal wiring is loose</li> </ol>	<ol style="list-style-type: none"> <li>1. Check power-on status</li> <li>2. Turn off the nearby lights or sensor head to other directions</li> <li>3. Reset</li> <li>4. Rewiring after power failure</li> </ol>
LED sensor light did not go out, continued to light up	Continuous movement within the sensing range	Check the relevant area and return or override the sensor head if necessary
LED sensor light illuminates during the day	The shadows around the sensor make it mistakenly think it's night	<ol style="list-style-type: none"> <li>1. Do not cover the sensor head</li> <li>2. Place the light in a place where the light is bright enough during the day</li> </ol>
LED sensor light flashing	Surrounded by other unstable light sources shining onto the induction	Avoid being exposed to such light sources
LED lights turn on unexpectedly	<ol style="list-style-type: none"> <li>1. Wind blows the branches and bushes within the sensing range</li> <li>2. Sensing cars on the road</li> <li>3. Sudden temperature change due to climate factors or fans, exhaust from open windows</li> </ol>	<ol style="list-style-type: none"> <li>1. Adjust its scope</li> <li>2. Adjust its scope</li> <li>3. Change irradiation area</li> </ol>

11

## FCC Warning:

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

**Note:** This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

HK JW Illumination Co., Limited  
Unit 616, 6/F., Kam Teem Industrial Building,  
135 Connaught Road West, Sai Wan Hong Kong  
Manufacturer/Hersteller: MDH LIGHTING LTD  
Suite 302, 292 Strovolos Avenue, 2048 Strovolos Nicosia,  
Cyprus

UK Importer: MDH LIGHTING LTD  
69 Aberdeen Avenue, Cambridge CB2 8DL,  
United Kingdom

Made in China

support@olafuslife.com www.olafuslife.com

