UPDATING YOUR ARCADE1UP CABINET

Series 3032 PCBA





What you will need:

- -Arcade1Up cabinet with a series 3032 PCBA
- -Phillips Head Screwdriver
- -Windows Computer
- -USB-A to microUSB
- -Corresponding Updater tool



Once the patch has been downloaded. Right click the folder then "Extract All"



First open the "Driver Update" folder

Run the "DriverInstall" application

Pin to Quick Copy Paste access	Paste shortcut	Move Copy Delete Rename to * to * *	New folder	Properties	tory 📑 Invert selection
Clipboard	t b	Organize	New	Open	Select
← → ~ ↑ 📕 >	Driver Update >			v O X	Search Driver Upd
Quick access	Name	^	Date	e modified	Туре
	ADB	Driver	12/4	/2020 12:00 PM	File folder
OneDrive	📜 bin		12/4	/2020 12:00 PM	File folder
This PC	Drive	er	12/4	/2020 12:00 PM	File folder
3D Objects	🕤 confi	g	6/3/	2014 1:38 AM	Configuration se
Deskt	🍮 Driv	शुInstall	7/26	/2019 12:15 AM	Application
Documents					
Downloads					
Music					
Pictures					
Videos					
😍 Blade (C:)					
Intwork					
S DESKTOP-265NE	40				
S LAPTOP-MM161	IQF				
S LAPTOP-TSO65Q	P5				



Run "Install driver" application Close once complete

If prompted by User Account Control select "Yes"

Pin to Quick Copy access	Paste Paste shortcut	Move Copy to * to * Org	Delete Rename	New folder New	Prop	ope	History	Binvert selection
$\leftarrow \rightarrow \sim \uparrow$	📕 > Driver Update >				~	Ö	و م	Search Driver Upd
 Quick acces OneDrive This PC 3D Object Desktop Document Download 	s ADB bin Drive s Conf s Orive	Driver er ig erInstall	K Driver Assitant	v4.91	Date modifi 12/4/2020 1 12/4/2020 1 12/4/2020 1 12/4/2020 1 6/3/2014 1:3	ied 2:00 Pf 2:00 Pf 2:00 Pf 2:00 Pf 2:00 Pf 2:00 Pf	M M M	Type File folder File folder File folder File folder Configuration s X
Pictures Videos Blade (C:)	265NE4O							

LAPTOP-MM161IQF

S LAPTOP-TSO65QP5



Open the "Updater" folder

Run the "Updater" application

access	Paste (Paste sh	ortcut to *	Copy to *	Delete Rename	New folder		Prop	erties	History	and the	rert selection
ç	lipboard		Org	janize	N	ew		Ope	n		Select
1	📕 > Updater >						.*	U		Search 1	Ipdater
	N	ame	~		Date	modified		Type			Size
# Quick acce	55	bin			12/4/.	2020 12:00 Pt	a	File	folder		
 OneDrive 		Language			12/4/	2020 12:00 P	VI.	File	folder		
This PC		Log			12/4/	2020 12:00 PI	vi.	File	older		
3D Object		config.cfg			9/16/	2020 11:57 A	M	CFG	File		2 Ki
Desisters	5	config			9/16/	2020 11:56 A	M	Con	liguration	setti	2 K
Desktop		Firmware			11/17	/2020 12:55 /	MA	Disc	Image Fi	le	52,736 K
Documen	its	Loader.bin			11/17	/2020 12:55 /	MA	BIN	File		183 K
		Updater			8/20/	2019 7:03 PM		App	lication		1,160 K
Music											
Fictures											
Videos											

Blade (C:)

DESKTOP-265NE4O

LAPTOP-MM161IQF

LAPTOP-TSO65QP5

KKDevTool v2.71 KKDevTool v2.71 KKDevTool v2.71 KKdress Naee Path Videococcoo Elouder Videococcoo Firmware Videococcoo Firmware Loader: Run Switch Dev Partition Clear No Devices Found	KKDevTool v2.71 Pornload Image Upgrade Firmeare Advanced Function O Monomono Easder O Monomono Firmeare Loader: Run Switch Dev Partition Clear No Devices Found	KKDevTool v2.71 Pernload Image Upgrade Firmware Advanced Function Address Name Path Concontrol v2.71 Concontrol	KKDevTool v2.71 Peralesed Image Upgrade Firmware Advanced Function Address Have Path O 000000000 Exader Concontrol v2.71 Concontrol v2.71 O 000000000 Exader Loader. Run Switch Dev Partition Clear No Devices Found	KKDevTool v2.71 Pevaleed Image Upgrade Firmware Advanced Function Address Name Path Address Name Path Concontrol Devices Found No Devices Found		Clipboard			Organize		new.	Opi	m	Select
RKDevTool v2.71 Pernload Image Upgrade Firmware Advanced Function Okconocococo Losdar Occonocococo Firmware Loader: Run Switch Dev Partition Clear No Devices Found	KKDevTool v2.71 Pornload Inage Upgrade Firmware Advanced Function Ox00000000 Lasder Ox00000000 Firmware Loader: Run Switch Dev Partition Clear No Devices Found	RKDevTool v2.71 Pereload Image Upgrade Firmware Advanced Function Address Have Path Obc00000000 Eineware Obc00000000 Firmware Loader: Run Switch Dev Partition Clear No Devices Found	RKDevTool v2.71 Pernload Image Upgrade Firmeare Advanced Function Address Name Path Ox00000000 Ensider Ox00000000 Firmeare Loader: Run Switch Dev Partition Clear No Devices Found	RKDevTool v2.71 Pevaload Inage Upgrade Firmware Advanced Function Address Name Path Conconnection Development of the sector o	÷	↑ <mark> </mark>	Updater	*			~	0	9	Search Updater
Deveload Inage Upgrade Firmeare Advanced Function	Deveload Image Upgrade Firmware Advanced Function Address Name Path Okonomono Firmware Okonomono Firmware Loader: Run Switch Dev Partition Clear No Devices Found	Deveload Inage Upgrade Firmware Advanced Function	Deveload Image Upgrade Firmware Advanced Function Address Hame Path Concontrol Pirmware Concontrol Pirmware No Devices Found	Deveload Inage Upgrade Firmeare Advanced Function	🔏 RKD	evTool v2.	71							
Address Name Path Address Name Path Concontrol Deconococo Lander Concontrol Pirmware Loader. Run Switch Dev Partition Clear No Devices Found	Address Newe Path Address Newe Path Okonomono Fireware Concological Concernation Concernation Clear No Devices Found	Address Name Path Address Name Path Ox00000000 Fireware Address Name Path No Devices Found	Address Name Path	Advanced Function	n -1									
Address Name Path Coordinate Path Dev Partition Clear No Devices Found	Address Name Path Ox00000000 Londer Ox00000000 Firmware Ox00000000 Firmware Loader: Run Switch Dev Partition Clear No Devices Found	Address Hase Path Ox00000000 Lasder V 0x00000000 Firmware Loader: Run Switch Dev Partition Clear No Devices Found	Address Hane Path Image: Optimized and optimized	Address Name Path Octoocococo Lander Octoocococo Fireware Loader: Run Switch Dev Partition Clear No Devices Found	Down	oad Image	Upgrade	Firmware Ad	lyanced Function					
Image: Source Found	Image: Character Image: Character Imag	Image: Source Source Jake Image: Source Source Source	Image: Control of the state Image: Contrel of the state Image: Contre	Image: Control of the state Image: Contrel of the state Image: Contre					P. 13					
2 Dot0000000 Fireware < Loader: Run Switch Dev Partition Clear No Devices Found	2 0x0000000 Fireware Coder: Run Switch Dev Partition Clear No Devices Found	2 Duttooooooo Fireware < Loader: Run Switch Dev Partition Clear No Devices Found	2 Duttooooooo Fireware c Loader: Run Switch Dev Partition Clear No Devices Found	2 V 0x0000000 Firmesre C C C C C C C C C C C C C C C C C C C		Ad Ad	iress	Nane	Fath					
< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear	Loader: Run Switch Dev Partition Clear No Devices Found	2	✓ 0x	00000000	Firnware						
< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear	Loader: Run Switch Dev Partition Clear No Devices Found				1	_					
Loader: Run Switch Dev Partition Clear No Devices Found	< Loader. Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear	Loader: Run Switch Dev Partition Clear No Devices Found										
Loader: Run Switch Dev Partition Clear No Devices Found	< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
Loader: Run Switch Dev Partition Clear No Devices Found	Loader. Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
Clear No Devices Found	Loader. Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
< Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	< <p>Loader: Run Switch Dev Partition Clear No Devices Found</p>	< <p>Loader: Run Switch Dev Partition Clear No Devices Found</p>										
< Clear No Devices Found	Kun Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found										
Clear No Devices Found	Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Clear No Devices Found	Kun Switch Dev Partition Clear No Devices Found										
Loader: Run Switch Dev Partition Clear	Loader: Run Switch Dev Partition Clear No Devices Found	Loader. Run Switch Dev Partition Clear No Devices Found	Clear No Devices Found	Clear No Devices Found										
Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found	Loader: Run Switch Dev Partition Clear No Devices Found							>			
No Devices Found	No Devices Found	No Devices Found	No Devices Found	No Devices Found				Run	Switch	Dev Partition	Clear			
No Devices Found	No Devices Found	No Devices Found	No Devices Found	No Devices Found	103	der								
No Devices Found	No Devices Found	No Devices Found	No Devices Found	No Devices Found	Loa	ider:								
No Devices Found	No Devices Found	No Devices Found	No Devices Found	No Devices Found	Loa	ider:								
					Loa	ider:								
					Loa	ider.		No De	vices Fou	nd				
					Loa	ider:		No De	evices Fou	nd			_	
					Loa	ider.		No De	evices Fou	nd				
					Loa	ider.		No De	evices Fou	nd			-	
					Loa	ider.		No De	evices Fou	nd				-
					Loa	ider.		No De	evices Fou	nd				-
					Loa	ider.		No De	evices Fou	nd				

Click the first box under

. . .



Select the "Loader" file then click "open"

	Clipboard		Organize	New		Oper	n	Select
÷ ~ 1	Updater	>			~	Ö	,	Search Updater
KRKDe	/Tool v2.71							
Downlo	ad Image Harrada	Firmers 1d	wanned Function					
_	an mage official	TTTTTTTTTTT	wanced runceson					
	Address	Nune	Path		-			
1	✓ 0±00000000	Loader	C:\Users\sr115\Deskt	p\Updater\Load				
2	I✔ 0x00000000	Firnware						
¢		-			2			
< Load	ler Ver 2.54	Run	Switch Dev P	utition Clear	>			
< Load	ler Ver 2.54	Run	Switch Dev Pa	artition Clear	>			
< Load	ler Ver:2.54	Run	Switch Dev Pa	utition Clear	>			
< Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	>			
< Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	>			
< Load	ler Ver 2.54	Run No De	Switch Dev Pa	urtition Clear	,			
< Load	ler Ver 2.54	Run No De	Switch Dev Pa	utition Clear	>			
Load	ler Ver.2.54	Run No De	Switch Dev Pa	artition Clear	>			
Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	>			
Load	ler Ver 2.54	Run No De	Switch Dev Pa	utition Clear	>			
Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	,			
Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	,			
Load	ler Ver 2.54	Run No De	Switch Dev Pa	artition Clear	,		Fil	
Load	ler Ver 2.54	Run No De	Switch Dev Pa	urition Clear	, , ,		fil	e
Load	ler Ver 2.54	Run No De	Switch Dev Pa evices Found	utition Clear	è.		fil	e
< Load	er Ver 2.54	Run No De	Switch Dev Pa	artition Clear			fil	e

Click the second box under "..."



Standing Arcade cabinet

Flip the switch to "OFF"



Standing Arcade cabinet

Plug in Micro USB Cable



ccess		Fabrad	to *	to • •	folder	•	History	and and
	C	lipboard		Organize	New	0	pen	
\rightarrow	Ť.	> Updater				~ 0	9	Search U
X	RKDev	Tool v2.71						
*		J Taxan IV I		1				
	OWILLOB	ad Inage Upgrade	Firnware Ad	wanced Function				
				n . 41		_		
		□ Address	Loader	C Wsers sr115 Deskto				
	2	▼ 0x00000000	Firnware	C:\Users\sr115\Deskto	op\Updater\Firm			
					Charles Contractore and a second s			
16								
4								
-								
○日本								
「「「「「「」」」	ĸ					•		
	< Loade	er Ver:2.54	Run	Switch Dev Pa	artition Clear	•		
	< Loade	er Ver.2.54	Run	Switch Dev Pa	artition Clear	•		
	< Loade	er Ver:2.54	Run	Switch Dev Pa	artition Clear	•		
	< Loade	er Ver.2.54	Run	Switch Dev Pa	artition Clear	•		

Once the USB is connected the bottom should say "Found one MASKROM Device"

Then click "Run"

2		opuner				· · · · · · · · · · · · · · · · · · ·	
RKDe	vToo	l v2.71					
ownlo	ad I	mage Upgrade	Firmware Ad	vanced Function	Download	Boot Start	
			_		Wait For	Maskrom Start	
		Address	Nane	Path	Wait For Test Dev	Maskrom Success ice Start	
2	Ť	0x00000000	Firnware	C:\Users\sr115\Desktop\Updater\Firm	Test Dev	ice Success	
					Check Ch	ip Start hin Success	
					Get Flax	hInfo Start	
					Get Flas Frepare	hInfo Success IDB Start	
					Prepare	IDB Success	
					Bownload	IDB Success	
					Wait For	Maskron Start Maskron Susaars	
					Test Dev:	ice Start	
<					> Start to	ice Success download Firmware	
1.000			Run	Switch Dev Partition Clear	Download	Firmware (100%)	
Loa	Jer vi	el.2.04			Download	image OK	
				N			
		Fo	und One	MASKROM Device			

When download = 100%. Close program







Remove Micro USB cable

Flip switch to "ON"

Connect power adapter

GAME ON !!!