

FM011 User Manual

INTEGRATED SMART FEATURES

Redefining Door Unlocking

 Living 3D fingerprint	 Anti-counterfeiting technology	 Encrypted Magnetic Card
 Anti Prying Alarm	 Scramble Pincode	 Low Battery Indication



1. Adding Master Password when Initial Use/ Enter Digital Setting

Step 1	Step 2	Step 3	Step 4
Press on “*” and then “#” to enter setting mode.	Enter a 6–8-digit password and press on “#” to confirm	Enter the same password again and press “#” to confirm. You will be sent into the setting mode	Press “*” to exit setting mode



2. User Manage (Adding Users/ Admin)

Step 1	Step 2	Step 3
<p>Press on "*" and then "#" to enter setting mode</p>	<p>Verify Admin and press "2" User Setting and press "1" Add User you may see the following options:</p> <ol style="list-style-type: none"> 1. Family 2. Nanny 3. Guest 4. Temp 	<p>Note: For add admin, you will not see the options from Step 2. You can just register using the following options below.</p> <p>Press any number from Step 2, The system will prompt you to Enter Unlock Information You may use the following options to register:</p> <ol style="list-style-type: none"> 1. Add Fingerprint 2. Add Password 3. Add Card 4. Add Wi-Fi Unlock

Step 4
<p>(1) Password</p> <p>Enter 6 pin number and press "#" Repeat the step once more.</p> <p>(2) Register Fingerprint</p> <p>Scan your preferred fingerprint 3 times to register.</p> <p>(3) Setting Up RFID card</p> <p>When prompted to input a new key, tap the RFID Card on the number pad area to complete setup.</p> <p>(4) Add remote control (USmartGo must be installed into your phone in order to use this function)</p> <p>The user presses any key of the remote control that needs to be added, and the voice prompt "add successfully"</p>



3. User Manage (Deleting Admin)

Step 1	Step 2	Step 3
Press on "*" and then "#" to enter setting mode	Verify Admin and press "1" for Admin Setting. Press "1" Delete Admin and you will see the following options: 1. Delete User By Number 2. Delete Other	1. Delete by ID The voice prompt "Please enter the user number to be deleted", the user can enter a three-digit user number, such as "001". If the user exists in the system, the voice prompt "Delete succeeded", if the user does not exist, the voice prompt "Operation failed" 2. Delete Other The System will show 2 options: Delete User Admin No (*) Yes (#)

4. User Manage (Deleting User)

Step 1	Step 2	Step 3
Press on "*" and then "#" to enter setting mode	Verify Admin and press "2" for User Setting. Press "2" Delete User and you will see the following options: 1. Delete User By Number 2. Delete User By Group	1. Delete by ID The voice prompt "Please enter the user number to be deleted", the user can enter a three-digit user number, such as "001". If the user exists in the system, the voice prompt "Delete succeeded", if the user does not exist, the voice prompt "Operation failed" 2. Delete User By Group The system will show: Input UserType 1. Nanny 2. Guest 3. Temp



5. System Setting (Set Time and Date)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin and press "3" System Setting	Press "1" Set Time and enter the details in the following format: YY : MM : DD HH : MM	Press "#" to confirm and Press "*" to exit setting mode

6. System Setting (Voice)

Step 1	Step 2	Step 3	Step 4
Press on "*" and then "#" to enter setting mode.	Verify Admin and press "3" System Setting	Press "2" Voice and you will see the following options: 1. On 2. Off	Press "#" to confirm and Press "*" to exit setting mode



7. Append Setting (Factory Reset)

Step 1	Step 2	Step 3	Step 4
<p>Press on "*" and then "#" to enter setting mode.</p>	<p>Verify Admin and press "4" Append Setting</p>	<p>Press "1" System Reset 1/2 and you will see the following options:</p> <ol style="list-style-type: none">1. No (*)2. Yes (#)	<p>Press "#" to confirm and</p> <p>Press "*" to exit setting mode</p>