



USER GUIDE FOR 360ANYWHERE

Shenyang TECHE Technology Co., Ltd.

ABOUT

360Anywhere, introduced by TECHE, is one of the first 360 cameras supporting 8K in-camera real-time stitching and live stream.

Jinhe Rao

Presented by Life Pal Limited, official representative of TECHE for global market.

Hardware Illustrations



Fisheye Lens

LED Screen

Shutter/Confirm

Power/Mode

Status Light



1/4 Interface



USB-C

1/4 Interface

DC Port

Ethernet Port

Technical Specifications

Model No.	FP1360/FP1363
Name	360Anywhere
Photo Output Formats	JPS/DNG
Video Output Format	MP4
Lenses	4 x F2.2 Fisheye Lenses
Photo Shooting	7,680 x 3,840
Video Recording	7,680 x 3,840 @30fps In-Cam Stitching: 7,680 x 3,840 @20fps 5,760 x 2,880 @25fps 3,840 x 1,920 @30/60fps
Live Streaming	Codec H.264 Max Bitrate 150Mbps Resolutions: 7,680 x 3,840 @20fps 5,400 x 2,700 @30fps 3,840 x 1,920 @30/60fps 7,680 x 3,840 @30fps (Live Streaming Edition 512GB)
Audio	Built-in Mic x 2; External Mic via USB-C
Video Color-Bit	10-bit & 8-bit
IP Rating	IP66; No Fan & Seamless Sealed Design; Passive Heat Dissipation System
Dimensions	155mm x 55mm x 55mm
Weight	approx. 420g (Live) and 620g (Pro)
Storage	256GB/512GB (Live); 512GB (Pro)
Connections	USB-C 1 Gbps Ethernet Built-in 5G 2x2 Wi-Fi
Battery	6,800mAh built-in battery (approx. 2.5 ~ 3h; Professional Edition only and no built-in battery for Live Streaming Edition); 12V 3A power adapter
Working Temperature	-20 C° to 40 C°

How to Use

1. Charge Camera

1) (Professional Edition) Equipped with 6,800mAh build-in battery and it takes about 5 hours for a full charge when the camera is off, which will last for about 2.5-3 hours shooting/recording/live streaming.

2) (Professional Edition) Use the power adapter to supply the power to the camera or charge the battery. (Live Streaming Edition) The camera is on automatically when it's connected to the power adapter. The status light goes green for standby.

3) (Professional Edition) Charge the camera when it's off. When the status light is constant red, it's charging the camera; When the status light is flashing, it's NOT charging the camera. Please disconnect it from the power and keep the camera cool down for about 15-30 minutes before you give it another try. The camera will protect itself from being charged when it's heated to guarantee that it won't get overheated and will be able to work 24/7.

2. Power On/Off

1) Power On: Long press the power button for 3 seconds to turn on the power; The status light is green when the camera stands by, and the status light is blue when it's working.

2) Power Off: Long press the power button for 3 seconds to turn off the power. The status light goes off when the camera has been shut down.

3) Force to Turn Off Power: Long press the power button for 10 seconds to turn off the camera. The status light goes off.

3. Main Lens

The main lens on the Main View side is located at the side with the product name 360ANYWHERE.

4. LED Screen

On the LED screen, camera's IP address, battery capacity, and the current mode will show up. You can switch the camera modes by pressing the power button. There are 4 modes available: Photo, Video, Live and USB.



5. Photo Shooting

- 1) Switch to Photo mode to start shooting.
- 2) Single press the shutter button to take a photo or long press the shutter button for the burst shooting.

6. Video Recording

- 1) Switch to Video mode and press the Shutter button to start recording.
- 2) Press the Shutter button again to stop recording.

7. Live Streaming

Configure the live streaming with TECHE CENTER App/PC Controller. Both Android and iOS apps are available. Search TECHE CENTER on iOS App Store or go to WWW.LIFEPALSTORE to download the Android installer.

8. USB-C Port

- 1) Connect the camera to your computer via USB-A to USB-C cable to download your footage. Press the mode button to confirm the selection until the following icon shows up on the LED screen. (The camera won't be charged, and you will need to use the file transfer software if you're using Mac OS)



2) Connect your microphone to the camera via USB-C to 3.5mm/OTG cable. Be noted that the audio profile is AAC LC.

9. Wi-Fi Setup

- 1) Search Wi-Fi SSID with your smartphone/computer for 360Anywhere
- 2) The password is: teche720 (You can't change the password)

10. TECHE CENTER & Connection to Computer

- 1) Connect both your computer and camera to the same network, like to the same ethernet router or the camera to the ethernet router while the computer to the Wi-Fi with the same network as the ethernet router.
- 2) Launch 360Anywhere Controller and the camera's IP address will show up in the Auto Search box or use the Manual to fill in the camera's IP address, Service Port: 8080 and Preview Port: 8554.

Useful Resources:

1. How to connect the camera to my computer/smartphone? [Read Now](#)
2. How to set up live streaming using third-party software? [Read Now](#)
3. How to set up live streaming with 360Anywhere Controller/TECHE Center? [Read Now](#)
4. Where can I download TECHE software? [Download Now](#)
5. Frequent asked questions about TECHE products. [Read Now](#)

Precautions

1. When connecting the power/ethernet cable to the camera, make use you've aligned the white dot on the connector to the one beside the DC/ethernet port before you push in the connector.
2. When pulling out the power/ethernet cable from the camera, pull out the safe rubber circle first before you pull out the connector. DO NOT turn the connector

around or use force to pull it out, which is not guaranteed by the [TECHE Warranty Policy](#).

3. Install the heat dissipation assistant to the top of the camera if necessary.
4. It's suggested that you turn the main lens to the major scene you want to show to your audience for better watching experience.
5. It's suggested that you install the camera at a place with 2 to 2.5 meters height to achieve the best watching experience for human eyes.
6. Remove the lens protection covers before you use the camera. Keep the camera lenses safe and DO NOT get them scratched, which is not guaranteed by the [TECHE Warranty Policy](#).

Contact Us

Website:

www.lifepalstore.com

Life Pal Limited

610 Nathan Road

Rooms 1318-19, Hollywood Plaza

Mongkok, Kowloon

Hong Kong SAR, China

Tel: +852 6061 8656; Email: support@lifepalstore.com

Shanghai Qianshou Network Technology Co., Ltd.

No 800 Naxian Road

Room 301-A3, Building 1

Pudong New Area, Shanghai 201210

China

Tel: +86 186 2158 7850; Email: joe@qsvrtech.com