



MODEL: L270  
Solar Security Floodlight |  
Motion Sensor | 80LED | PARAMOUNT

For more information visit

[hoselink.com.au](https://www.hoselink.com.au)

or call

1300 900 617

Cultivating **Connections**

 [youtube.com/hoselink](https://www.youtube.com/hoselink)



# User Manual

MODEL: L270  
Solar Security Floodlight |  
Motion Sensor | 80LED | PARAMOUNT

**HOSELINK**<sup>®</sup>

## Kit Contents

---

1 x Motion Sensor Solar Wall Light

## Lighting Modes

---

### 1 Medium light mode (flashes once)

Light automatically comes on at dusk and off at dawn.

Motion sensor will not be active on this setting.

### 2 Dim light sensor mode (flashes twice)

Continuously emits a dim light (18 LEDs) from dusk until dawn, with a bright light for 15-20 seconds when motion is detected.

### 3 Bright Sensor mode (flashes three times)

Light remains on standby mode until motion is detected then a bright light will emit for 15-20 seconds.

## Activate the Light

---

To activate the light, click the IO button on the side of the light. The button with the M printed on it will allow you to change between lighting modes.

Test by covering the solar panel completely to check that the light comes on. The light is now ready for use.

## Product Installation

---

### STEP 1 Find a suitable location

Solar lights need access to direct sunlight for optimum results; preferably 6-8 hours per day. The motion sensor will detect movement up to 5m away.

### STEP 2 Install the light

## Installation - Option 1

---

Using adhesive outdoor tape.

Adhere using Hoselink Outdoor Acrylic Double-Sided Tape (SKU L100), sold seperately. Be sure to stick the tape onto the stainless-steel plate on the back of the light.

## Installation - Option 2

---

Using supplied hardware.

Use a 6mm drill piece for masonry installation. Once your

hole is drilled, gently hammer the plugs into place and then secure the screws tightly. For timber, use a 3mm drill piece without the plugs. Hang the light and enjoy.

Be sure to clean the solar panel periodically to maintain optimal performance.

## Specifications

---

Solar panel	5V / 1.7W
LED Lumens	300 lumens (bright light)
Light Temperature	6500 kelvins
Lithium Battery	2000mAh / 3.7V
Charge Time	8 hours
Working Time	Up to 90 hrs depending on light mode

**NOTE:** if the light does not turn on, this could be due to the battery not being charged. Leave out in direct sunlight for 6-8 hours and try again.