

LED SLIM FIT RECESSED DOWNLIGHTS - CCT SELECTABLE INSTALLATION INSTRUCTIONS

Items:

RDL/4RND/9/5CTS RDL/6RND/12/5CTS RDL/6RND/12HL/5CTS

! Caution READ AND FOLLOW ALL SAFETY INSTRUCTIONS


1. DANGER- Risk of shock- Disconnect power before installation.
2. This luminaire must be installed in accordance with the NEC or your local electrical code.
3. Suitable for wet location and in ambient temperatures not exceeding 104°F
4. Not for use in hazardous environments
5. Min 167°F supply conductors
6. This luminaire is rated for 90-130V/AC 50/60HZ only.
7. Do not install if lens is cracked, or fixture is damaged in any way

Product data

Voltage: 90-130VAC
Frequency: 50/60Hz
Power factor: ≥ 0.9
Operating temperature: 14°F to 104°F

Dimming- This unit is designed to be compatible with most leading-edge incandescent or LED style dimmers. (Dimming range 100% - 5%). Fixture performance may vary depending on dimmer manufacturer and circuit loading. For an up to date dimmer list visit www.topaz-usa.com.

Dimensions



Model#	Driver			Luminaire	
	A	B	C	D	H
RDL/4RND/9/5CTS	3.43"	3.46"	1.3"	4.8"	0.71"
RDL/6RND/12/5CTS	3.43"	3.46"	1.3"	6.8"	0.83"
RDL/6RND/12HL/5CTS	3.43"	3.46"	1.3"	6.8"	0.83"

Installation steps

*Note -Slide dip switch to proper CCT setting before installing

1. Turn Power off at breaker or fuse before starting installation
2. Cut hole in ceiling according to dimensions above
3. Connect AC wire
4. Install fixture into ceiling
5. Re-connect power, turn on fixture; installation complete

2. Before installation, slide the dip switch to the desired color temperature at the driver box

Color selectable switch

Color selectable by dip switch

2700K-3000K
3500K
4000K-5000K

2. (a) Insert and rotate slotted screwdriver clockwise to remove top cover

(b) Open side knockout of the junction box with slotted screwdriver

1. Cut hole in ceiling (please see table for measurements)

3a. Connect wires
White wire is connected to N; black wire is connected to L; and yellow wire is connected to G

3b. You may mount the connection box/driver box to a joist in the ceiling or leave it loose above the fixture.

4. Install light into ceiling

Our Slim Recessed Downlights can be used in drop ceilings if tile is capable of supporting the load. Use installation frame-in kits (RDL4-FRAME KIT or RDL6-FRAME KIT) to provide support as necessary.