

# Outdoor Stand-Alone / Wiegand Keypad with Proximity Reader

SK-2612-SPQ Keypad and Proximity Card Reader

#### Features:

- 1,000 Users (up to 998 users and 2 duress users)
- User code length 4~6 digits
- 9~18 VDC Operation, low current draw 105mA max.
- Form C relay output 2A@12VDC
- Adjustable output time 0.5~99s, or toggle
- Built-in tamper alarm and external alarm (duress) output
- Backlit keypad and multicolor status LED
- EM 125kHz\*
- Easy transfer of users to additional devices using Wiegand output
- All features programmed directly on the keypad: No need for an external programmer
- · Egress input lets users exit the premises without a code/card
- Can serve as either Wiegand reader or controller, both output and input are selectable 26~37 bits
- 2-Door interlock function
- Extreme cold tolerance to -40° F (-40° C)
- Epoxy-filled black ABS plastic housing Weather-resistant IP66









1,000 Users

## **Specifications:**


Operating voltage		9~18 VDC
Current draw	Standby	40mA@12VDC
	Active	105mA@12VDC (max.)
Outputs	Form C	NO/NC/COM, 2A@12VDC
	Alarm	Transistor ground, 2.5A@12VDC,
	Wiegand	26~37 bits, PIN output bits – 4, 8, or 10
Inputs	Egress	N.O. Ground
	Door Sensor	N.C. Ground
	Wiegand	26~37 bits, PIN output bits – 4, 8, or 10
Card type		EM 125kHz
Enclosure / IP Rating		Epoxy-filled black ABS plastic, IP66
Operating temperature		-40°~140° F (-40°~60° C)
Dimensions		1 <sup>15</sup> / <sub>16</sub> "x4 <sup>3</sup> / <sub>4</sub> "x <sup>15</sup> / <sub>16</sub> " (49x120x24 mm)
Weight		5.8-oz (165g)

## SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

**Phone:** (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com

### **Dimensions:**



FC ( E 🚳

Copyright © 2020 SECO-LARM U.S.A, Inc. All rights reserved.

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

<sup>\*</sup>Proximity cards or key fobs available from SECO-LARM