



Control Panel Comparison Chart

Feature	SP4000	SP5500	SP6000	SP65	SP7000
StayD support	✓	✓	✓	✓	✓
4-wire expansion bus	✓	✓	✓	✓	✓
Maximum zones	32	32*	32*	32*	32*
On-board zones	4 (8 with ATZ)	5 (10 with ATZ)	8 (16 with ATZ)	9 (18 with ATZ)	16 (32 with ATZ)
Expansion zones	24	24	24	24	16
Keypad zones	15	15	15	15	15
Partitions	2	2	2	2	2
User codes	32	32	32	32	32
PGMs	12 (1 on-board)	16* (2 on-board)	16* (2+2** on-board)	16* (3 on-board)	16* (4 on-board)
PGM +/- trigger	-	-	✓	✓ (via BabyWare)	✓
Alarm relay	-	-	1**	-	1
Event buffer	256	256	256	256	256
Wireless expansion (RTX3)	✓ (one-way transmitters only)	✓	✓	✓	✓
Wireless expansion (RX1)	✓	✓	✓	✓	✓
2-wire smoke detector input	-	-	✓	-	✓
GPRS / GSM module (PCS series)	✓	✓	✓	✓	✓
IP100 compatibility	✓	✓	✓	✓	✓
VDMP3 compatibility	✓	✓	✓	✓ (via PCS200)	✓
REM3 support (requires RTX3 V1.31 or higher)	-	✓	✓	✓	✓
Patented 2 opto-coupler dialer circuit (US Patents 5751803, RE39406)	✓	✓	✓	-	✓
In-field firmware upgradable	✓	✓	✓	✓	✓
Menu-driven programming for Installer, Master, and Maintenance codes	✓	✓	✓	✓	✓
Multiple phone numbers: 3 for monitoring station, 5 for personal dialing, 1 for pager reporting	✓	✓	✓	✓ (via PCS200 only - SMS reporting)	✓
Automatic Daylight Savings Time	✓	✓	✓	✓	✓
Push button software reset	✓	✓	✓	✓	✓
Switching power supply	1.1A	1.1A	1.5A	1.1A	1.5A
Fits in 20 x 25.5 x 7.6 cm (8x 10 x 3 in) and 28 x 28 x 7.6 cm (11 x 11 x 3 in) metal boxes	✓	✓	✓	✓	✓

*Any of which can be wireless

** Optional