

Sensors Pack

Color Sensor

- [Datasheets](#)
- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Flame Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Hall Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)
- [Datasheets](#)

Infrared Reflective Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Laser Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Liquid Level Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Moisture Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

MQ-5 Gas Sensor

- [Datasheets](#)
- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Rotation Sensor

- [User Manual](#)

- [Schematic](#)
- [Code](#)
- [Software](#)

Sound Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

DHT11 Temperature-Humidity Sensor

Introduction

Temperature-Humidity Sensor, DHT11 Onboard

Features

Sensor	DHT11 (Temperature & humidity sensor)
Operating voltage	3.3V-5.5V
Humidity measuring range	20%-95% (0°C-50°C)
Humidity measuring error	+ -5%
Temperature measuring range	0°C-50°C
Temperature measuring error	+ -2°C

Dimensions	29.0mm*18.0mm
Fixing hole size	2.0mm
Table 1. Product features	

Applications

This module can be applied to environmental temperature & humidity measurement.

Interfaces

Pin No.	Symbol	Descriptions
1	DOUT	Communication port
2	GND	Power ground
3	VCC	Positive power supply (3.3V-5.5V)
Table 2. Interface specification		

How to use

We will illustrate the usage of the module with an example of temperature-humidity measurement by connecting a development board.

- Download relative codes to the development board.
- Connect the development board to a PC via a serial wire and the module to the development board. Then, power up the development board and start the serial debugging software. The configuration of the connection between the module and the development board are shown in Table 3 and Table 4.

Port	STM32 MCU pin
DOUT	GPIOA.0
GND	GND
VCC	3.3V

Table 3. The connection between STM32 development board and DHT11

Port	Arduino pin
DOUT	D2
GND	GND
VCC	5V

Table 4. The connection between Arduimo and DHT11

The configuration of the serial port is listed in Table 5.

Baud rate	115200
Data bits	8
Stop bit	1
Parity bit	None

Table 5. Serial port configuration

- Run the serial debugging software, then you can see relative data of humidity and temperature are outputted. For example:

```
Humidity=33
```

```
Temperature=28
```

Resources

- [Datasheets](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

Tilt Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Software](#)

UV Sensor

- [User Manual](#)
- [Schematic](#)
- [Code](#)
- [Datasheets](#)
- [Software](#)