

Technical specifications

| | |
|---|--|
| <p>Communication with control panel or range extender</p> <p>Jeweller communication technology</p> <p>Frequency bands 866.0-866.5 MHz 868.0-868.6 MHz 868.7-869.2 MHz 905.0-926.5 MHz 915.85-926.5 MHz 921.0-922.0 MHz Depends on the region of sales.</p> <p>Maximum effective radiated power (ERP) Upto 20 mW</p> <p>Communication range up to 1,300 m Without obstacles.</p> | <p>Compatibility</p> <p>Hubs all Ajax hubs</p> <p>Range extenders all Ajax radio signal range extenders</p> |
| <p>Compliance with special fire standards</p> <p>EN 50131 (Grade 2) PD 6662:2017</p> | <p>Features</p> <p>4 buttons Arm Disarm Night mode Panic Panic button can be deactivated by PRO or a user with admin rights in the Ajax apps.</p> <p>LED indication green and red SpaceControl reports its status only after any button is pressed.</p> <p>Protection against accidental press double or long press Configured by the PRO or user with admin rights in the Ajax apps.</p> |

| | | | |
|-----------------------------------|---|---------------------|---|
| <p>Anti-sabotage protection</p> | <p>Protection against spoofing device authentication</p> | <p>Power supply</p> | <p>1 x CR2032 battery Up to 5 years of battery life.</p> |
| <p>Enclosure and installation</p> | <p>Dimensions 65 x 37 x 10 mm</p> <p>Weight 13 g</p> <p>Operating temperature range from -25°C to +50°C</p> <p>Operating humidity up to 95%</p> <p>Protection class IP50</p> <p>Colours Black White</p> | <p>Complete set</p> | <p>SpaceControl Jeweller 1 x CR2032 battery Pre-installed Quick Start Guide</p> |