


Technical specifications

Compliance with standards	EN 50131 (Grade 2) PD 6662:2017	Compatibility	Hubs all Ajax hubs Range extenders all Ajax radio signal range extenders
---------------------------	--	---------------	---

<p>Communication with control panel and range extenders</p>	<p> Jeweller communication technology</p> <p>Frequency bands 866.0 - 866.5 MHz 868.0 - 868.6 MHz 868.7 - 869.2 MHz 905.0 - 926.5 MHz 915.85 - 926.5 MHz 921.0 - 922.0 MHz Depends on the region of sales.</p> <p>Maximum effective radiated power (ERP) :::20 mW</p> <p>Communication range up to 1,500 m 1n an open space.</p> <p>Polling interval 12 - 300 s Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Protection against forgery Device authentication</p>	<p>Features</p>	<p>Alarm type acoustic and light</p> <p>Alarm volume from 85 to 113 dB ata distance of 1 m Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Alarm duration from 3 to 180 s Adjusted by PRO or user with admin rights in the Ajax app.</p> <p>Siren sound frequency 3.5 ± 0.5 kHz</p> <p>Chime The siren makes a special sound to notify that the opening detectors are triggered when the system is disarmed.</p>
<p>Power supply</p>	<p>Main power supply 4 x CR123A battery Pre-installed</p> <p>Optional power supply 12 <u>V---</u>, 1.5 A</p> <p>Battery lite up to 5 years</p>	<p>Installation</p>	<p>Operating temperature range from -25°C to +60°C</p> <p>Operating humidity up to 95%</p> <p>Protection class IP54</p>

Enclosure

Colours

white, black

Dimensions

75 x 76 x 27 mm

Weight

97 g

Anti-sabotage

tampering alarm

Triggered when the device
body is opened.

accelerometer

Activated when someone's
try to move or dismount
the device.

Complete set

StreetSiren Jeweller

4 x CR123A battery

Pre-installed

SmartBracket

1 installation kit

Quick Start Guide
