

MIXER AMPLIFIER | MA-6Z360 AMPLIFIER

6 ZONE MIXER AMPLIFIER 360W WITH
ZONE VOLUME CONTROL, WITH MPLAYER C

ALHAAN



FEATURES:

► Controls

Front : 4 Input Channel Volume Control and 1 selectable source input
Volume control, Master Volume Control, 6 Zone Speaker Selector
with 6 step attenuator.

Rear : Talkover Switch (VOX) & Phantom Power Switch for Channel 1-4.
Chime enable with volume control.

Bypass contact input & system mute.

► Connectors

Input : Channel 1 - 4 : Electronically Balanced with chime switch.

Aux : Dual RCA.

Remote Mic : RJ45.

Emergency Alarm input : Euro block

Output : Speaker Output : Euro Block . Attenuated and Switched 6 CH,
Direct Output 4Ω, 8Ω, 70V, 100V.

REC Out & Link out : RCA.

Contact : Ext. Chime : Euro block.

MUTE : Euro block

► Media player module : FM Tuner / Recordable MP3 / bluetooth player.

► Indicators : SIG, -10dB, CLIP & Protect.Zone selector.

► Protection : Output Current Limiting, Thermal Protection & DC Offset
Protection.

► Cooling : Convection Cooling.

► Option : Rack Mount Kit.



TECHNICAL SPECIFICATION

| MODEL | | MA-6Z360 |
|-------------------------------|----------------------|---|
| RATED POWER (RMS) | | 360W |
| Input sensitivity / Impedance | Channel 1-4 | -36dB / -10dB Selectable / 20 kΩ Balanced |
| | Aux | 0dB / 20 kΩ Balanced |
| | Remote Mic | 0dB / 20 kΩ Balanced |
| Output level / Impedance | Speaker Output Hi-z | 100V (28Ω), 70V (14Ω) |
| | Speaker Output Low-z | 54V (8Ω), 38V (4Ω) |
| | Rec Out | 0dB / 600Ω Unbalanced |
| | Link Out | 0dB / 600Ω Unbalanced |
| Frequency Respose (-3dB) | | 65Hz - 18kHz |
| T.H.D (1kHz, Rated Power) | | <1% |
| Signal to Noise Ratio | | >80dB |
| Tone Control | ± 10dB | 100Hz , 10KHz |
| Power Source | | AC 115 / 230 V, 50/60Hz |
| Weight (Net) | | 11 kg |
| Dimensions (W x H x D) | | 420 x88 x 320mm |

