

## HPA OnePORT XDEVICE Reset/Dual Use Instructions

The following instructions are to reset the OnePORT if it has been incorrectly paired with the wrong ECU type or to unlock the OnePORT for dual use (DSG & ECU).

## **INSTRUCTIONS:**

- 1) Download the HPA OnePORT XDEVICE software through the link provided in your email. Unzip and install X-Device.
- 2) After installation, plug in your OnePORT with the provided USB cable to your PC run XDEVICE (on your desktop).
- 3) Click on the "Refresh List" button:

and the ID #	VDD				EVICE ON 8 T		
Location IV #	XDEN	ILE Name		XU	EVICE SN & Typ	0e	Refrest
nfiguration	License	Credits	End User	Security	Diagnostics	. History	USB
Coded Device	Information			- Initial De	evice Information		
Serial Number : 0			Serial Number : 0				
Device Type : Unknown Link to Device SN : 0			Link to Device SN : 0				
Shared Link SN : 0			Shared Link SN :				
Last Coding I	Date: N	o Date		Produc	tion Date :	No Date	
Device Firmw	are :						
Current Firm	ware version	1:	A0141027	7	Update	Firmware	
Device Firmy	vare version	1	FFFFFFFF				



4) You should now see the OnePORT information populate under "Location ID #" and "XDEVICE Name". Double click on this field:

Location ID #	ICE Name	CAN	XDEVICE SN & Type			Befrech Lie	
LOC. 10 #17	ADEV	ICE USB KP	CAN				
onfiguration Lie	ense	Credits	End User	Security	Diagnostics	s History	USB
Coded Device Inf	ormation	-		-Initial De	vice Informat	ion :	
Serial Number :	0			Serial N	lumber :	0	
Device Type :	Ur	known		Device	Туре :	Unknown	
Link to Device SI	1: 0			Link to	Device SN :	0	
Shared Link SN :	0			Shared	Link SN :		
Last Coding Date	: No	Date		Produc	tion Date :	No Date	
Device Firmware	:						
Current Firmwar	e version	:	A0141027	,	llode	ato Eirmuraro	
Device Firmware	version		FFFFFFF		Upda	ate Firmware	

5) The software will load the information from the OnePORT. Once you see the fields populated under the "Configuration ..." tab, click on "Click HERE for XDEVICE Configuration and Reference Numbers !!!":

CEVICE List ( Dou	ble Click	on an item to	read its data )	:			
Location ID # XDEVICE Name		XD	XDEVICE SN & Type				
Loc. ID #17	XDEV	ICE USB Kp	CAN	16	766 - END USI	ER	Refresh List
onfiguration Li	cense	Credits	End User	Security	Diagnostics	History	USB
-Coded Device In	formation			Initial De	evice Informati	ion :	
Serial Number : 16766			Serial Number : 16766				
Device Type : END USER			Device Type : END USER				
Link to Device SN : 12651			Link to Device SN : 12651				
Shared Link SN : 12651			Shared Link SN :				
Last Coding Date : 19/03/17 03:41:18			Produc	tion Date :	09/12/15 19:	11:56	
Device Firmware	ı:						
Current Firmwa	re version	1:	A014102	7	linds	ta Firmwara	
Device Firmwar	e version	-	A014102		opua	no i i i i i i i i i i i i i i i i i i i	
						the second value of the se	



6) This will bring you to a screen with the XDEVICE Coding. Click on "Copy Reference Numbers":

XDEVICE Tool Kit Version 1.0.0, Build 0077							
XDEVIC	XDEVICE Coding		×				
Locati	Reference Numbers :						
Loc. II	Configuration Reference Number :	16766-3607776213-58F54F33	ish List				
	License Update Reference Number :	16766-944317390-667643832-58F54F33					
Configur	Credits Update Reference Number :	16766-1873203820-58F54F33					
Connigur	End User Reference Number :	16766-3607776213-65535-58F54F33					
Code	Security Reference Number :	16766-3607776213-58F54F33					
Devia Link	Paste the Coding String here :	A					
Shar Last							
- Devic Curre		Ŧ					
Devi	Copy Reference Numbers	Execute Cancel					

7) Paste the copied information into and email and forward it to HPA. The information should look like this:



8) With this information, HPA will provide you with a Coding String through email. You will need to copy and paste the string into the "Paste the Coding String here" field:

	(DEVICE Coding	×	
Locati	Reference Numbers :		
Loc. II	Configuration Reference Number :	16766-3607776213-58F553DD	ish Lis
_	License Update Reference Number :	16766-944317390-667643832-58F553DI	
- Faur	Credits Update Reference Number :	16766-1873203820-58F553DD	
oningun	End User Reference Number :	16766-3607776213-65535-58F553DD	
Code	Security Reference Number :	16766-3607776213-58F553DD	
Shar Last Devic Curri		*	
Devi	Copy Reference Numbers	Execute Cancel	

9) Your OnePORT is now reset/unlocked.