## DUALLY D2

INSTRUCTIONS

THANK YOU AND CONGRATULATIONS ON PURCHASING A DUALLY D2 LED LIGHT! WITH RIGID'S PATENTED "SPECTER OPTICS", THE DUALLY D2 PROVIDES THE HIGHEST LUMEN OUTPUT AVAILABLE IN A COMPACT SOURCE. THE MOST ADVANCED LED LIGHTING TECHNOLOGY AVAILABLE TO DATE. THANK YOU FOR SUPPORTING RIGID INDUSTRIES AND ENJOY YOUR NEW LED LIGHT!

## IN THE BOX:

A = M6 NYLON LOCKNUTS (2)

B = MOUNTING BRACKET

C = M6 ALLEN BOLT (2)

D = DUALLY D2
CARRIAGE BOLT

CARRIAGE WASHER 5/16" CARRIAGE NUT

WIRING HARNESS

## 

FUSE CHART		
<u>LIGHT</u>	DUALLY D2	DUALLY D2 (PAIR)
AMPS	10	15





INSERT MOUNTING BRACKET INTO SLOTS AS SHOWN IN PICTURE. INSERT M6 NYLON LOCK NUTS INTO CAVITIES IN HOUSING. INSERT M6 ALLEN BOLTS INTO HOLES IN HOUSING, CAPTURING NYLON LOCKNUTS. SNUG SLIGHTLY AND MOUNT LIGHT USING CARRIAGE BOLT, WASHER AND NUT SYSTEM THAT WAS PROVIDED. WAIT TO SECURE ALL NUTS UNTIL YOU HAVE YOUR LIGHT WORKING AND IN DESIRED POSITION.

ATTACH RED TERMINAL TO BATTERY +, OR ANY 12VDC SOURCE. SECURE BLACK TERMINAL TO A SUITABLE GROUND OR BATTERY NEGATIVE. ROUTE HARNESS TO DESIRED SWITCH AND MOUNTING LOCATIONS, SECURE WITH ZIP TIES. BEWARE OF SHARP EDGES, ABRASIVE SURFACES AND HEAT SOURCES WHEN ROUTING WIRES. USE DIAGRAM BELOW TO VERIFY CORRECT WIRING TO SWITCH. USE THE FUSE CHART

ABOVE TO ASSURE CORRECT FUSE.

When installing Rigid Industries lights on a 24V system, be sure to use a 24V relay. When installing multiple lights, be sure you have adequate fusing. You will need 5 more amps of fusing for every Dually or dually D2. Finally, test light(s) to ensure proper operation. Contact technical support for questions regarding installation or light use. (480) 655-0100

