

MotionGrey


















**electric height adjustable
desk**



ASSEMBLY & USE INSTRUCTIONS

90.014.01.0496v.A

CAUTION / INFORMATION

- | | | | | |
|---|---|---|---|--|
|  | Make sure no obstacles are in the desk's path.
Make sure the desktop is not touching any walls.
Make sure all cords are appropriate length to accommodate the change in height. |  |  | WARNING
Pinch Point
Keep hands and fingers clear. |
|  | Keep children away from electric height-adjustable desks, control units and handsets. There is a risk of injury and electric shock. |  | | |
|  | Keep all electrical components away from liquids. |  | | |
|  | Do not sit or stand on the desk frame.
Do not crawl or lie under the desk frame. |  | | |
|  | Do not place any objects taller than 20" underneath the desk. |  | | |
|  | Do not open any of the components - the Legs, Control Box, or Switch.
There is a danger of electric shock. |  | | |
|  | This product is designed with a duty cycle of 10%
(2 min. on, 18 min. off). |  | | |
|  | In the event of a power outage or if the power cord is unplugged,
a manual reset may be necessary - see USE section. |  | | |

USE / LIABILITY

This height adjustable desk has electric motors and is designed for use in dry work areas only.

The desk height is adjustable so that it can be positioned at the most ergonomically suitable height.


Any other use is at user's risk.

Under no circumstances does the manufacturer accept warranty claims or liability claims for damages caused from improper use or handling of the desk frame.

IMPORTANT:
Please read this manual carefully.
If this desk is sold, please provide this manual to the buyer.

ASSEMBLY


TOOLS




PARTS LIST

Part	Qty	Part	Qty	Part	Qty
1 Leg	2	2 Foot	2	10 M6x10 Machine Screw	16
6 Control Box	1	3a Frame End-CB	1	11 M6x14 Machine Screw	12
7 Handset	1	3b Frame End	1	12 M5x20 Wood Screw	9
8 Power Cord	1	4 Center Rail	2	13 Cable Clip	10
9 4mm Allen Wrench (included)	1	5 Side Bracket	2		

ASSEMBLY




- 1 Lay out all components and hardware to ensure that you have all the components and hardware listed on the parts page. Slide the Control Box (part 6) off the Frame End-CB (part 3a) and set aside. Fully separate Frame End (part 3b) from Frame End-CB (part 3a). You will find the Center Rails (part 4) inside.



- 2 Place one of the Legs (part 1) into the Frame End-CB (part 3a) ensuring that the bar (arrow) is on "top" in relation to the Leg (part 1).
Line up the holes on the Leg (part 1) with the holes on the Frame End-CB (part 3a).
Using the supplied Allen Wrench, insert four (4) M6x10 Machine Screws (part 10) through the holes in the Frame End-CB (part 3a), going into the Leg (part 1) and rotate each screw just a few turns. After all four (4) M6x10 Machine Screws (part 10) are inserted, tighten all four (4) screws.


Do the same for the other Leg (part 1) and the Frame End (part 3b).

i if you drop a screw inside the frame end, simply tilt to retrieve. **i**




- 3 The Frame End-CB (part 3a) should be placed on the side of the desk where you plan to mount the Control Box (part 6) and the Handset (part 7).
Slide the Side Bracket (part 5) into the Frame End-CB (part 3a). Insert two (2) M6x14 Machine Screws (part 11) through the two (2) holes in the bottom of the Frame End (part 3a) going into the inserted Side Bracket (part 5). Using the supplied Allen Wrench, rotate each screw just a few turns. After both M6x14 Machine Screws are inserted, tighten both screws.

Do the same for the other frame end/leg assembly.




- 4 Slide the two (2) Center Rails (part 4) into the two Frame Ends (parts 3a & 3b) ensuring:
a) the slots in the Center Rails (part 4) face inward
b) the slots in the Center Rails (part 4) are closer to the top edge when the assembly is upside down (see inset).



- 5 For each leg assembly, attach a Foot (part 2) with four (4) M6x14 Machine Screws (part 11) and tighten in a cross-pattern.


ASSEMBLY



6

Your desktop may or may not be pre-drilled. Check both sides of the desktop before placing the desk base on the underside of the desktop.

Adjust the width of the desk base to fit the desktop by sliding the two halves outward. We recommend leaving at least 1/2" of the desktop width (on each end) protruding beyond the frame width and centering the Side Brackets (part 5) fore and aft.




7

If the desktop is pre-drilled, perform Step 8 before Step 7.

If the desktop is not pre-drilled, lock the position of the Center Rails (part 4) using eight (8) M6x10 Machine Screws (part 10).

⚠ Ensure that the M6x10 Machine Screws (part 10) contacts the Center Rails (part 4) by sliding the Center Rails (part 4) as needed. ⚠



8

⚠ Double-check that the wood screws are not too long for your desktop and won't puncture the surface when screwed all the way in. ⚠


i We recommend that you pre-drill any holes needed for fasteners if your desktop is not pre-drilled. Never use countersunk screws. i

Double-check that the desk base is properly positioned on the underside of the desktop.

Attach the desk base to the underside of the desktop using seven (7) M5x20 Wood Screws (part 12).

Attach the Handset (part 7) so the front of the handset is flush with the front desktop edge (or recessed up to 1/8"). The handset may be placed anywhere along the front edge of the desktop but we recommend placing it toward an end so it does not interfere with your chair when seated. Use two (2) M5x20 Wood Screws (part 12) to attach the handset to the desktop.

⚠ Do not overtighten screws in this step. ⚠
Overtightening could cause damage to the components. ⚠



9

Slide the Control Box (part 6) onto the Frame End-CB (part 3a).

Connect the cable exiting the Leg (part 1) that is attached to the Frame End-CB (part 3a) directly into the Control Box (part 6).

Connect the Cable (part 9) to the other Leg (part 1) and to the Control Box (part 6).

Connect the Handset (part 7) cable to the Control Box (part 6).

Use the adhesive-backed Cable Clips (part 14) to secure the cables so they do not sag.

ASSEMBLY

- 10 Turn the assembled desk right-side up. With at least two people, grab the DESK BASE (not the desktop) and turn the desk right-side up. Adjust the pre-installed glides on the Feet (part 2) as needed.