

Transmitter Combiners 700 -1000 MHz Transmitter Combiners TXC4x3y-z Series

TXC4233-1 3 CH Ultra High Q Ceramic Transmitter Combiner 763-776 MHz

- Field tunable
- Down to 150 kHz Tx-Tx spacing
- Low loss: 2.9 dB (typ) at minimum spacing
- Compact 3U height

The ceramic combiner uses an ultra high Q ceramic resonator. This simultaniously allows for a very low loss within the combiner and a very close spacing between the transmitter frequencies. The compactness of the resonator means that up to 3 channels can fit in a 3U high, 14 inch deep envelope.

This combiner comes in 1, 2 and 3 channel modules. Combiners with larger numbers of channels can be built by joining these modules.

The loss of a 3 channel combiner as a function of the transmitter spacing is listed below:

| Minimum Tx-Tx spacing | Maximum Insertion Loss | Typical Insertion Loss |
|-----------------------|------------------------|------------------------|
| 150-250 kHz | 3.4 dB | 2.9 dB |
| 250-500 kHz | 2.8 dB | 2.4 dB |
| > 500 kHz | 2.5 dB | 2.1 dB |

If the combiner is to be used in an earthquake zone or other high vibration environment then additional support brackets can be ordered. See the ordering information in the next page.



| Region | United States | Europe, Middle East and Africa | Caribbean and Latin America | Canada and rest of the world |
|--|-----------------------|--|--------------------------------|--|
| Telephone | USA: 1 800 263 3275 | International: +44 (0) 1487 84 28 19 | International: +1 905 726 7676 | Canada: 1 800 263 3275 International: +1 905 727 0165 |
| E-mail | salesusa@sinctech.com | salesuk@sinctech.com | salesla@sinctech.com | salescan@sinctech.com |
| Product Specification Sheet EPR 018780 Customer Tech Manual 006416 | | TXC4233-1 Sinclair's commitment to product leadership may result in i | Issue: 5 | Dated: 31-05-19 Dated: 07-11-16 |

air's commitment to product leadership may result in improvement or change to this produc Copyright © Sinclair Technologies



A Norsat Company 🔟 Norsat

Transmitter Combiners 700 -1000 MHz Transmitter Combiners TXC4x3y-z Series

| Electrical Specifications | | | |
|-----------------------------------|-----|-----------------|----|
| Frequency Range | MHz | 763 to 776 | |
| Number of channels | | 3 | *1 |
| Input Connectors | | N-Female | |
| Output Connectors | | 7/16 DIN-Female | |
| Input VSWR (max) | | 1.25:1 | |
| Output VSWR | | 2:1 | |
| Insertion loss (typ) Tx to Ant | dB | 2.4 | *2 |
| Insertion Loss (max) Tx to Ant | dB | 3.4 | *3 |
| Maximum Input Power (per channel) | W | 125 | |
| Frequency separation (min) | MHz | 0.15 | |
| Isolation Tx to Tx | dB | 70 | |
| Isolation antenna to Tx | dB | 60 | |
| | | | |

Notes

*1 : Can be expanded using multiple modules

*2 : 250-500KHz spacing, see table in the previous page

*3 : see table in the previous page

Ordering Information

Optional brackets: TXC-MKIT-0003-3 (qty. 2)

Mechanical Specifications

| Width | in (mm) | 19 (483) | |
|----------------|----------|--------------|--|
| Depth | in (mm) | 14 (356) | |
| Length/ Height | in (mm) | 5.25 (133) | |
| Weight | lbs (kg) | 23.5 (10.67) | |

°F (°C)

| Environmental | Specifications |
|---------------|----------------|

Temperature range

+14 to +140 (-10 to +60)

| Region | United States | Europe, Middle East and Africa | Caribbean and Latin America | Canada and rest of the world |
|---|-----------------------|---|--------------------------------|--|
| Telephone | USA: 1 800 263 3275 | International: +44 (0) 1487 84 28 19 | International: +1 905 726 7676 | Canada: 1 800 263 3275 International: +1 905 727 0165 |
| E-mail | salesusa@sinctech.com | salesuk@sinctech.com | salesla@sinctech.com | salescan@sinctech.com |
| Product Specification Sheet EPR 018780 | | TXC4233-1 | Issue: 5 | Dated: 31-05-19 Dated: 07-11-16 |
| Customer Tech Manual 006416 | | Sinclair's commitment to product leadership may result in improvement or change to this product | | |

air's commitment to product leadership may result in improvement or change to this product Copyright © Sinclair Technologies