



LiFePO₄

PRODUCT MANUAL

Lithium Iron Phosphate Battery



12.8V
50Ah

Marine | Smart 
FOR TROLLING MOTOR & MORE
BLUETOOTH 5.0
(50A BMS)



 www.redodopower.com
 service@redodopower.com



PRODUCT OVERVIEW

12.8V 50Ah Battery

Operating Voltage: 12.8V


Charging Voltage: $14.4 \pm 0.2V$

Recommended Charge Current: 10A (0.2C)

Max Continuous Discharge Current: 50A

Max Continuous Load Power: 640W


Max. Thrust Power: 70lbs




Additional Components

M8- 35/64" [14mm] Terminal Bolts

The terminal bolts are used to secure multiple cable lugs to a single battery terminal. The bolts can be replaced with [M8](#) bolts of other lengths based on actual needs.



Insulating Caps for Bolts





BATTERY-PACK MAIN PARAMETERS

Item	Parameter
Cell Type	LiFePO4
Nominal Voltage	12.8V
Rated Capacity	50Ah
Energy	640Wh
Internal Resistance	≤40mΩ
Cycle Life	≥4000 times
Battery Management System (BMS)Board	50A
Charge Method	CC/CV
Charge Voltage	14.4±0.2V
Recommended Charge Current	10A (0.2C)
Max. Continuous Charge Current	50A
Max. Continuous Discharge Current	50A 60A@30mins
Surge Discharge Current	250A@ 1 second

Item	Parameter
Max. Continuous Output Power	640W
Max.Thrust Power	70lbs ^①
Dimension	L7.80 * W6.54 * H6.69 inch L198 * W166 * H170 mm
Housing Material	ABS (Flame Retardant Plastic)
Recommended Terminal Torque	106.2 to 123.9 inch·lbs/ 12 to 14 N·m
Protection Class	IP65
Temperature Range	Charge: 0°C to 50°C / 32°F to 122°F Discharge: -20°C to 60°C / -4°F to 140°F Storage: -10°C to 50°C / 14°F to 122°F
Low Temperature Charging Protection (LTCP) Function ^②	Yes
Resume Charging Temperature Under LTCP	5°C/41°F (Battery Temperature)
FCC ID	2BE5H-12V50

① One 12V 50Ah Smart Bluetooth Marine for Trolling Motor battery is suitable for 12V trolling motors up to 70 lbs thrust; 2*identical batteries in series for 24V trolling motors up to 100 lbs thrust; 3*identical batteries in series for 36V trolling motors up to 120 lbs thrust.

② The 12V 50Ah Smart Bluetooth Marine for Trolling Motor battery supports Low Temperature Charging Protection(LTCP), where the BMS stops battery charging when the battery temperature falls below 0°C/32°F and resumes charging when the temperature rises above 5°C/41°F.



HOW TO ESTIMATE THE BATTERY CAPACITY


STATE OF CHARGE (SOC)

The battery capacity could be roughly estimated by its [resting voltage \(not charging/discharging voltage\)](#)^①.

Since the voltage of each battery is slightly different, and the voltage measurement is affected by the measuring instrument, ambient temperature, etc., [the following parameters are for reference only](#). The actual SOC of the battery is based on the discharge capacity under load.

Resting Voltage: The voltage is measured after the battery has been disconnected from the charger and loads with zero current, and left alone for 3 hours.

VOLTAGE(V)



SOC (%)	VOLTAGE (V)
0	10 to 12
25	13 to 13.15
50	13.15 to 13.2
75	13.3 to 13.33
100	≥ 13.33 ^②

- ① Based on the characteristics of LiFePO₄ batteries, the voltage measured by all LiFePO₄ batteries during charging/discharging is not the real voltage of the battery. Therefore, after charging/discharging and disconnecting the battery from the power source, the voltage of the battery will gradually drop/increase to its real voltage.
- ② After this battery is protected from overcharge, the tested battery voltage (not the real voltage) will be lower than the real voltage. To calculate the SOC (%), add 0.5V to 0.7V to the tested battery voltage.



SERIES / PARALLEL CONNECTION

THE PREMISE OF CONNECTION

To connect in series or /and parallel, batteries should meet the below conditions:

- identical batteries with the same battery capacity (Ah) and BMS (A);
- from the same brand (as lithium battery from different brands has their special BMS);
- purchased in near time (within one month).

LIMITATION FOR SERIES/PARALLEL CONNECTION


Support connecting up to 16 identical batteries for up to:

4 in series as 48V (51.2V) battery system/

4 in parallel as 200Ah battery system.


Series Connection

48V(51.2V) 50Ah




Parallel Connection

12V(12.8V) 200Ah





WHAT TO DO WHEN THE BATTERY STOPS WORKING?



It has 85% chances that BMS has shut it off for protection, and you could try one of below ways to activate the battery.

General Steps

If the BMS has cut off the battery for protection, follow the below steps to activate it.

Step
1

[Cut off](#) all the connections from the battery.

Step
2

[Leave the battery aside for 30mins](#)

Then the battery will automatically recover itself to normal voltage (>10V) and can be used after fully charged.

If the battery is unable to recover itself after the above steps, please try activating by **ONE OF BELOW TWO METHODS.**

After activated (voltage > 10V) and fully charged by the normal charging method, it can be used normally.

Method ①

Use a [charger with lithium battery activation function](#) to fully charge the battery.

Method ②

Connect a [controller](#) that supports 12V LiFePO4 battery charging to charge the battery for 3~10s in sunny daytime.



PROVIDER

Shenzhen Maicheng Technology Innovation Co., Ltd.

MANUFACTURER CONTACT

service@redodopower.com