

**SIMPLE SPI CONTROLLER**



CODE  
BL-PC-SPI16M16

- FUNCTION
- Simple control for use in dynamic SPI LED neon applications
  - Can be used with BL-LS-4200-RGBC and BL-LS-4700-RGBC
  - 15 preset modes, can adjust brightness, direction, and speed of lighting
  - RF remote included, 2.4GHz, up to 40 metres

OUTPUT	MAX. LOADING	VOLTS
	50W	5V DC
10A or 1023 pixels	120W	12V DC
	240W	24V DC

ADDITIONAL POWER SUPPLY REQUIRED FOR LOAD MORE THAN 10A. REFER TO INSTALLATION GUIDE WIRING DIAGRAM

DIMENSIONS	Receiver
	W30 × L135 × H20mm
DIMENSIONS	Remote
	W58 × L104 × H9mm

HOUSING PVC casing

MOUNTING 2 × mounting tabs

WARRANTY 5 years

COMPLIANCE 

OPERATING TEMP. -20°C ~ +55°C

INGRESS PROTECTION Indoor use only

CONNECTION METHOD Screw terminals

CONTROL SPI signal

MAX. DISTANCE FROM POWER SUPPLY Recommended under 10 metres  
For specific projects contact Bright Light