

# RA series Transfer Switches



The RA Automatic Transfer Switch is integrated with the RS series genset. These products are Listed to UL 1008, the Standard for Transfer Switch Safety. The switch and generator set combination is specifically designed for a simplified, quicker installation.

These UL 1008 switches are suitable for standby power systems in residential and light commercial applications. These RA products adhere to National Electrical Code (NEC) and National Fire Protection Association (NFPA) requirements.

The RA transfer switch monitors utility power 24 hours a day and 7 days a week. When utility power becomes unsatisfactory or fails; the generator set is signaled to start, then automatically transfers the load. When stable utility voltage returns, the transfer switch will automatically switch electrical load from the generator to the utility. No action is required by the home owner.

The RA switch is also available in Service Entrance models. A service entrance version is also UL 1008 listed and makes use of a UL 489 listed circuit breaker.

## Features

### **Mechanically interlocked contactor**

- Long-life, high pressure, silver alloy contact resists burning and pitting
- A powerful and economical solenoid drives the mechanism

### **UL 489 Listed circuit breaker**

- Square D

### **Solid bus bar connection**

- Between circuit breaker and transfer switch

### **Neutral and ground bar**

- Fully rated
- Bonding jumper on neutral and ground
- Silver plated copper ground and neutral bus

### **Ease of connection**

- Solderless screw type terminals for external power connections

## Transfer switch mechanism



- A powerful and economical solenoid powers RA Transfer Switches.
- Independent break-before-make action is common for 2-pole.
- Mechanical interlock prevents simultaneous closing of normal and emergency contacts.
- Electrical interlocks prevent simultaneous closing signals to normal and emergency contacts and interconnection of normal and emergency sources through the control wiring.
- Long-life, high pressure, silver alloy contacts resist burning and pitting. Contacts are mechanically held in both normal and emergency positions for reliable, quiet operation.

## Specifications

<b>Voltage rating</b>	Transfer switches up to 240 VAC, 50 Hz or 60 Hz.
<b>Amperage rating</b>	Transfer switches rated for 100 and 200 continuous amperes.
<b>Arc interruption</b>	Multiple leaf arc chutes cool and quench the arcs. Barriers prevent interphase flashover.
<b>Neutral bar</b>	A full current-rated neutral bar is standard on enclosed 2-pole transfer switches.
<b>Auxiliary contacts</b>	Two contacts rated at 5A continuous at 100 VAC or 2.5A continuous at 200 VAC (one for each source) are provided for customer use. Wired to terminal block for easy access.
<b>Storage temperature</b>	-25° C (-13° F) to 55° C (131° F)
<b>Humidity</b>	Up to 90% @ 20° C
<b>Altitude</b>	Up to 2,000 m (6,561 ft) without derating
<b>Total transfer time (source-to-source)</b>	Will not exceed 100 msecs with normal voltage applied to the actuator.
<b>Manual operation handles</b>	Transfer switches are equipped with a removable operating handle which allows operation during servicing in order to facilitate troubleshooting with sources of power disconnected

## UL 1008 withstand and closing ratings

Transfer switch ampere	Coordinated molded case breakers
100A	22,000
200A	22,000
100A SE	10,000
200A SE	10,000

## Enclosures

Wire bend space complies with 2011 NEC.

### Dimensions - transfer switch in UL type 3R enclosure

Model and Amp rating	Height		Width		Depth		Weight		Outline drawing
	in	Mm	in	mm	in	mm	lb	kg	
100 A	24.0	619	17.0	433	7.4	187	33	15	A044R213
200 A	27.1	688	18.2	463	7.4	187	46	21	A044R213
100A SE	23.3	591	19.8	503	7.2	182	58	26	A044R213
200A SE	23.3	591	19.8	503	7.2	182	58	26	A044R213

## Transfer switch lug capacities

Model and Amp rating	Size
100A	#14 AWG to 2/0 CU/AL
200A	#6 AWG to 300 MCM CU/AL

## Service entrance transfer switch lug capacities

Model and Amp rating	Size		
	Utility	Load, neutral and generator	Ground
100A SE	#4 AWG to 300 MCM CU/AL	#14 AWG - 2/0 CU/AL	#14 AWG - 1/0 CU/AL
200A SE	#4 AWG to 300 MCM CU/AL	#6 AWG - 300 MCM CU/AL (transfer switch and neutral only) #14 AWG - 2/0 CU/AL (generator)	#14 AWG - 1/0 CU/AL

## Submittal details

Description	Part #	Rating	Voltage	Enclosure
RA112N3	A045P692	100 A	120/240 V 1 phase	3R
RA212N3	A045P694	200 A	120/240 V 1 phase	3R
RA112S3	A045P696	100 A SE	120/240 V 1 phase	3R
RA212S3	A045P697	200 A SE	120/240 V 1 phase	3R

## Certifications



All switches are UL 1008 Listed with UL Type Rated cabinets and UL Listed CU-AL terminals.



All switches comply with NEMA ICS 10.



All switches comply with NFPA 70, 99 and 110.



**Our energy working for you.™**  
[www.cumminspower.com](http://www.cumminspower.com)

**North America**  
1400 73rd Avenue N.E.  
Minneapolis, MN 55432 USA

Phone 763 574 5000  
Fax 763 574 5298

**Asia Pacific**  
10 Toh Guan Road #07-01  
TT International Tradepark  
Singapore 608838

Phone 65 6417 2388  
Fax 65 6417 2399

**Brazil**  
Rua Jati, 310  
Guarulhos – Sao Paulo  
CEP – 07180-140

Phone 55 11 2186 4195  
Fax 55 11 2186 4729

**Europe, CIS, Middle East & Africa**  
Manston Park Columbus Ave.  
Manston Ramsgate  
Kent CT 12 5BF United Kingdom

Phone 44 1843 255000  
Fax 44 1843 255902

Specifications are subject to change without notice.

©2013 Cummins Power Generation. All rights reserved. Cummins Power Generation and Cummins are registered trademarks of Cummins Inc. PowerCommand, InPower and "Our energy working for you." are trademarks of Cummins Power Generation.