



SG10208

**10-Port 10/100/1000Base Switch
with (8) 1000Base SFP Slots**

User's Manual v2.1

© December 2019
VERSITRON, Inc.
83 Albe Drive / Suite C
Newark, DE 19702
www.versitron.com

PROPRIETARY DATA

All data in this manual is proprietary and may not be disclosed, used or duplicated, for procurement or manufacturing purposes, without prior written permission by **VERSITRON**.

VERSITRON LIFETIME WARRANTY

All VERSITRON products are covered by a **Lifetime Warranty** against defects in materials and workmanship. This coverage is applicable to the original purchaser and is not transferable.

We repair, or at our option, replace parts/products that, during normal usage and operation, are proven to be defective during the time you own the products, provided that said products and parts are still manufactured and/or available. Such repair/replacement is subsequent to receipt of your product at our facility and our diagnostic evaluation and review of the unit. Advance replacements are not provided as part of the warranty coverage.

This warranty does not cover damage to products caused by misuse, mishandling, power surges, accident, improper installation, neglect, alteration, improper maintenance, or other causes which are not normal and customary applications of the products and for which they were not intended. No other warranty is expressed or implied, and VERSITRON is not liable for direct, indirect, incidental or consequential damages or losses.

In the unlikely event a warranty issue should arise, simply contact us at 302-894-0699 or 1-800-537-2296 or via email at fiberlink@versitron.com to obtain a Return Material Authorization (RMA) number, along with instructions for returning your product.

1. Overview

The **SG10208** 10-Port 10/100/1000Base Switch supports two 10/100/1000Base copper ports and eight 1000Base fiber optic SFP slots. The switch is designed with a switch controller and buffer memory that allows the two media types to operate smoothly. The RJ-45 copper ports supports 10/100/1000Mbps and Half-Duplex or Full-Duplex modes, while the eight fiber optic SFP slots support 1000Mbps and Full-Duplex only. With an external power unit, the **SG10208** provides excellent stability and reliability.

2. Checklist

Before installing the **SG10208**, verify that the package contains the following:

1. (1) **SG10208** 9-Port Switch.
2. (1) AC-DC Power Adapter.
3. This User's Manual.

Please notify VERSITRON immediately if any of the aforementioned items are missing or damaged.

3. LED Descriptions



LED	Description
SPD	Lit when TP speed is 1000Mbps
ACT	Lit when TP connection is good Blinks when TP data is transmitting
P1-8	Lit when SFP1-8 connection is good OR when SFP1-8 data is transmitting
PWR	Lit when power is applied

4. Installing the SG10208 Switch

1. Install a fiber optic SFP module into one or all of the SFP Slots.
2. Connect the fiber optic cable from the SFP module on the **SG10208** to the fiber network.
NOTE: Confirm that the fibers are connected Transmitter to Receiver.
3. Connect a UTP cable from the TP network device to the RJ-45 port on the **SG10208**.
4. Connect the power adapter to the **SG10208** and check that the Power LED lights up. The TP Act and SFP LEDs will light accordingly when all cable connections are correct.

5. Technical Specifications

- **Standards:** IEEE 802.3, 802.3ab, 802.3i, 802.3u, 802.3x, 802.3z
- **UTP Cable:** Cat.5e or Cat.6 cable up to 100m
- **Fiber Cable:** 1000SX: 50/125, 62.5/125µm multi-mode
1000LX/ZX: 8/125, 9/125µm single-mode
- **Data Transfer Rate:** RJ-45 ports: 10M, 100M, 1000Mbps
SFP: 1000Mbps
- **LED Indicators:** P1, P2, P3, P4, P5, P6, P7, P8, SPD, ACT, PWR
- **Duplex Modes:** RJ-45 ports: Half/Full-Duplex auto-negotiation
SFP: Full-Duplex mode
- **Power Requirements:** Input: 100 ~ 240VAC, 50/60Hz, Output: 15VDC, 2A
- **Operating Temperature:** 0 ~ 50°C
- **Storage Temperature:** -20 ~ 70°C
- **Humidity:** 5% ~ 90%
- **Dimensions:** 7.48 x 4.10 x 1.14 inches (L×W×H)

6. Available Fiber Optic SFP Modules

Model	Speed (Mbps)	Wavelength	Media	Distance	Connector	TX Power	RX Sens	Temp
GBMM	1000	850nm	MMF	62.5μ: 220m 50μ: 550m	LC	-9.5 ~ -4	< -18	0 to 70° C
GB2MM	1000	1310nm	MMF	2km	LC	-9 ~ -1	< -19	0 to 70° C
GB10SM	1000	1310nm	MMF / SMF	MM 62.5μ: 220m MM 50μ: 550m SM 9μ: 10km	LC	-9.5 ~ -3	< -20	0 to 70° C
GB20SM	1000	1310nm	SMF	20km	LC	-4 ~ +1	< -24	0 to 70° C
GB40SM	1000	1550nm	SMF	40km	LC	-4 ~ +1	< -24	0 to 70° C
GB70SM	1000	1550nm	SMF	70km	LC	0 ~ +5	< -24	0 to 70° C
GB100SM	1000	1550nm	SMF	100km	LC	0 ~ +5	< -30	0 to 70° C
GB10SFA	1000	Tx: 1310nm Rx: 1550nm	SMF	10km	LC	-3 ~ -9	< -21	0 to 70° C
GB10SFB	1000	Tx: 1550nm Rx: 1310nm	SMF	10km	LC	-3 ~ -9	< -21	0 to 70° C
GB20SFA	1000	Tx: 1310nm Rx: 1550nm	SMF	20km	LC	-3 ~ -8	< -23	0 to 70° C
GB20SFB	1000	Tx: 1550nm Rx: 1310nm	SMF	20km	LC	-3 ~ -8	< -23	0 to 70° C
GB40SFA	1000	Tx: 1310nm Rx: 1550nm	SMF	40km	LC	-3 ~ +2	< -23	0 to 70° C
GB40SFB	1000	Tx: 1550nm Rx: 1310nm	SMF	40km	LC	-3 ~ +2	< -23	0 to 70° C
GB60SFA	1000	Tx: 1310nm Rx: 1550nm	SMF	60km	LC	0 ~ +5	< -24	0 to 70° C
GB60SFB	1000	Tx: 1550nm Rx: 1310nm	SMF	60km	LC	-2 ~ +4	< -25	0 to 70° C
GB80SFA	1000	Tx: 1310nm Rx: 1550nm	SMF	80km	LC	-2 ~ +3	< -26	0 to 70° C
GB80SFB	1000	Tx: 1550nm Rx: 1310nm	SMF	80km	LC	-2 ~ +3	< -26	0 to 70° C