

BCM Radio to Arcom RC-210

Cable used: Belden 9537

Color	Function	BCM Radio	RC-210
Black	GND	15	8
Orange	COS Out	10	Q1 Base
White	Rx Discrim Out	9	5
Blue	Tx Audio In	5 – 6.8K-10K	4
Red	+5V from Radio	12	1.2 K -> Pin 7
Green	Not used		
Brown	PTT Input	8	3
Shield	Shield – GND	15	8

If assigned to PORT2 or 3, set PORT2 JP2 or PORT3 JP4 for Active HIGH.

RX Audio Jumper needs to be FLAT.

Cable wiring is as follows:

