

Key Features

- Distributes L band frequency signals to multiple GPS synchronization modules and receivers
- High Isolation
- Excellent Gain Flatness
- DC power sourced from any GPS receiver via any port

Benefits

- Optimum signal quality with low noise
- Rugged, providing long-lasting, trouble free deployment
- High isolation mitigates interference between multiple GPS devices
- Features reliability and redundancy

Customers who bought this Item also bought



L1AW
L1 GPS Reference Antenna

Reliable Time Through Design

GPS Source is the market leader for high quality GPS components. Our reputation has been earned by designing ruggedized equipment for military applications. All GPS Source splitters are designed and manufactured to military specifications.

The S14GT L1 Active Splitter distributes GPS, Galileo, GLONASS, BeiDou and Compass frequencies to four outputs. This enables a single timing reference antenna and cable configuration to sync multiple systems.

Its high isolation mitigates interaction between multiple GPS receivers including oscillation.

Any single output port connected to a VDC source can power both device and active GPS antenna. The S14GT is designed to automatically switch to another port supplying DC voltage should the initial port fail or the DC source is removed.

The S14GT delivers a simple redundant design, ensuring uninterrupted DC voltage to the splitter and the active antenna, eliminating requirements for a separate power supply or wiring, lowering equipment and installation costs.



Table 1-1. Electrical Specifications

Operating Temperature -40°C to 85°C

Parameter	Conditions	Min	Typ	Max	Units
Frequency Range ⁽¹⁾	Ant: Any Port; Unused Ports: 50Ω	1.1		1.7	GHz
Gain	Ant: Any Port; Unused Ports: 50Ω (Gain can be 0dB or 10dB)	-3	0	+3	dB
Input/Output SWR	All Ports 50Ω		2:0:1		—
Noise Figure	Ant: Any Port; Unused Ports: 50Ω, Gain = 0dB			2	dB
Gain Compression Point (IP1dB)	Gain = 0dB	-35			dBm
3rd Order Intercept (IIP3) (Gain = 0dB)	f1 = 1600.42MHz f2 = 1625.42MHz 2f1 - f1 = fL1	-24			dBm
RF Input (Damage Threshold)	Max RF Input Without Damage			0	dBm
Amp. Balance	[J1 – J2] Ant: Any Port; Unused Ports: 50Ω			1	dB
Phase Balance	Phase (J1 – J2) Ant: Any Port; Unused Ports: 50Ω			1	Degree
Delay - Amplified	Ant: Any Port; Unused Ports: 50Ω, L1			5	ns
Isolation - Amplified (Gain = 0dB)	Adjacent Ports: Ant – 50Ω	30			dB
	Opposite Ports: Ant – 50Ω	40			dB
DC IN	DC Input on any RF Output	3.3		12	VDC
Device Current	Current Consumption of Active Device (excludes Ant. Cur.)		18	20	mA
Ant/Thru Current ⁽²⁾	Max Source DC Current Through Device			250	mA

- Notes: 1. Frequency range includes GPS L1, GLONASS L1, GALILEO E1
 2. Maximum current available from the DC source through the S14GT when output of S14GT is short circuited.

