

2 channels electronic time switch weekly cycle


ref.: 23142
ref.: 23152



Major characteristics

- Product delivered with current time and date set.
- Automatic change of winter/summer time $\ast/\#$.
- Programming key .
 - for permanent override,
 - for program copy or save.
- Programming for day or group of days.
- 56 program steps On, Off.
- Permanent overrides On or Off (permanent light on)
- Temporary overrides On or Off (flashing).
- Display bar graph of daily profile.
- Keyboard locking possible .
- Programmable with power off.

Key



- 1 menu:** selection of operating mode
auto: mode of running according to the program selected.
prog new: for programming mode.
prog modif: to modify an existing program.
<: checking of the program.
⊙: modification of time, date and selection of the winter/summer time change mode.
- 2 + and -:** navigation or setting of values.
C1 : in **auto** mode, selection of overrides.
C2
- 3 enter:** to validate flashing information on display.
- 4** : to return to the previous step.
You may return into **auto** mode at any moment using menu. If no action is taken for 1 min, the switch returns into **auto** mode.

Technical specifications

Electrical characteristics

- Supply voltage: 230V AC \pm 15%
- Frequency: 50/60 Hz
- Power consumption: max. 0,5 VA to 50 Hz
- Output: 2 changeover volt free contacts
- Maximum load: AC1 μ 16A 250V~
Cos φ = 0,6 μ 10A 250V~
- Incandescent lighting: 2300 W
- Halogen lighting 230V: 2300 W
- Compensated fluorescent tubes \parallel (max. 45 μ F): 400 W
- Non compensated fluorescent tubes, compensated in series: 1000 W
- Compact fluorescent lamps: 500 W
- Minimum current: AC1: 100 mA 250V~
- Galvanic insulation between power supply and output: 4 kV
- Degree of pollution: standard

Functional characteristics


- Programming capacity: 56 steps
- Minimum time between 2 steps: 1 minute
- Running accuracy: \pm 1,5 sec/24h
- Operating reserve: lithium battery provides 5 years of backup.
- The product is set into standby state (display switched-off) after 1 minute with power off. It switches back into auto mode as soon as power is back or when pressing any key.
- Protection degree: IP20

Environment


- Operating temperature: -5 °C to +45 °C
- Storage temperature: -20 °C to +70 °C

Connection

- Flexible capacity: 1 to 6 mm²
- Rigid capacity: 1,5 to 10 mm²



Connection diagram




Reset

- **Resetting the program:** the program can be totally deleted by pressing the following three keys simultaneously: **menu**, **enter** and , the time and date are retained.
- **Reboot:** pressing the **+**, **-**, **menu** and **enter** keys simultaneously reboots the product.

Programming: prog new

Programming may be done for each day or for a group of days. In this case instructions are common to several days.

Days: 1 = Monday, 2 = Tuesday, 3 = Wednesday... 7 = Sunday.



1. Select the **prog** mode using **menu**, then **enter**. New mode selected validate with **enter**. The number of remaining program steps appears for a short time. The first step of the first day or group of days appears.
2. Select the channel (A or B) using **+** or **-**. Validate with **enter**. The number of remaining program steps appears for a short time.
3. Select the day(s) using **+** or **-**. Validate with **enter**.
4. **ok** flashes. Use **enter** to validate the group.
5. Using **+** or **-**, select the state of the instruction: On, Off. Use **enter** to validate state.
6. Enter the hours of switch-on using **+** or **-**. Validate with **enter**.
7. Enter minutes with **+** or **-**. Validate with **enter**. Program the other instructions of the group of days by repeating operations 3 to 7. The day or the group of days may be modified at the during step 2 by pressing the **+**, **-** or **←**.

At the end of programming return to **auto** mode using the **menu** button. To set the program of the other channel, return to **prog new** mode and proceed according to steps 2 to 7.

In this mode it is also possible to add an instruction to the program set up.

Proceed as described above.

Display <

To check the daily profile set up without the risk of modification or deletion: select the mode < using **menu** and press **enter**. The first step of Monday is displayed as well as the daily profile.

Two options available for display:

1. Pressing repeatedly **+** or **-**: lets you shift days. In this case only the first daily step is displayed as well as the daily profile.
2. Pressing **enter**: all steps of each day appear one after the other.

Modification or clearing of a program step: prog modif

Select the **prog** mode with **menu** and press **enter**. Select the **modif** mode with **+** or **-**. Validate with **enter**.

The number of remaining program steps appears for a short time. The first step of the first day or group of days appears.

Repeatedly pressing the **enter** key displays all programmed steps one at a time. Any flashing field (state, hour, minutes) may be modified using **+** or **-**, then validated with **enter**.

When the cursor is positioned on **ok** located behind the group of days, you may display successively the days or the groups of days and switch directly to the one that has to be modified using **+** or **-**.

To remove a program step: select the state of the channel (On or Off), press simultaneously **+** and **-**. **Clear** appears on the screen. Validate with **enter**.

At the end of programming, return to **auto** mode using the **menu** button.

Key ⌨ (only ref. 23152)

As soon as the key is inserted into the switch, ⌨ appears on the screen.

Two types of operation:

A. Permanent override:

Insert the key into the switch.

After 10 seconds the program contained in the key will be executed without clearing the program contained in the time switch.

As soon as the key is removed the program of the time switch is again valid.

B. Copy (load)/Save (save):

The key makes it possible to save a program contained in the time switch.

It is also possible to copy the contents of the key into the clock.

1. Insert the key and wait for 2 sec.

2. Using **menu** select the mode:

save to save a program contained in the time switch.

load to load the program of the key into the time switch, to check the program contained in the key.

3. Validate the selection with **enter**.

4. For **save** and **load** reconfirm with **enter**.

The following error messages may appear on the screen:

no prog: the key is empty, it does not contain any program.

Error: the key is that of a one-channel switch.

In these two cases:

- Only the save save to key is possible.
- The error message remains on display as long as the key is present, but in this case the program of the time switch is executed.

Setting time and day ☺

Winter/summer time change *!#

Select the mode ☺ with **menu** then **enter**.

Modify the day, month, year, the hour and the minutes using **+** or **-** and **enter**. The time switch next suggests the winter/summer time changes *!#.

Select the type of change desired using **+** or **-**.

Validate with **enter**.

The type of change depends on the geographical zone.

* type according defect

Type	Start of time change Summer	Start of time change Winter	Zone of application
Euro*	Last Sunday in March	Last Sunday in October	European Union
USA	First Sunday in April	First Sunday in November	North America
USER	Date freely programmed	Date freely programmed	
No	No change	No change	

Types available:

The change always takes place between 2:00 and 3:00 a.m.

When the **USER** type is selected:

1. Enter the day then the month of the date of change of the summer time (+ 1 hour) with **+** or **-** and **enter**.
2. Enter the day then the month of the date of change of the winter time (- 1 hour) with **+** or **-** and **enter**.

The time switch will check which days of which weeks correspond to these dates and will apply changes to the same periods for the following years independently of the date.

Override

Pressing repeatedly C1 ☺ or C2 ☺

If the state of the output is **On**:

1st press: temporary override. **Off** and ☺ flash. The next program step will let you return to the automatic mode.

2nd press: permanent override. **On** and ☺ are permanent. This override must be cancelled manually.

3rd press: permanent override. **Off** and ☺ are permanent. This override must be cancelled manually.

4th press: return to the automatic mode.

Locking ⏹

To prevent all undesirable actions, the keyboard of the time switch may be locked using a key ref. 23193 or pressing the **enter** and **←** keys for 7 seconds.

Unlocking is done in the same way.