

## Installation Instructions for the Sure-Lites LED Emergency Driver

---

### WARNING

---

#### Risk of Fire/Electric Shock

If not qualified, consult an electrician.

---

### WARNING

---

#### Risk of Electric Shock

Disconnect power at fuse or circuit breaker before installing or servicing.

---

### IMPORTANT SAFEGUARDS

WHEN USING ELECTRICAL EQUIPMENT, BASIC SAFETY PRECAUTIONS SHOULD ALWAYS BE OBSERVED INCLUDING THE FOLLOWING.

#### 1. READ AND FOLLOW ALL SAFETY INSTRUCTIONS

2. Do not use outdoor
3. Do not use near gas or electric heaters.
4. Do not use in air handling heated air outlets, sealed and gasketed fixtures, wet or hazardous location fixtures.
5. Do not let power supply cords touch hot surfaces.
6. Do not use this equipment for other than the intended use.
7. The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition. Servicing should only be performed by qualified service personnel.
8. Equipment should be mounted in locations and at heights where it will not readily be subjected to tampering by unauthorized personnel.
9. Prior to installation, battery connector must be open to prevent high battery drain on the unit .
10. This product is for use with an emergency LED lighting load and supplies nominally 7.5 W of power with a voltage of 15-50V in emergency mode, for a minimum of 90 minutes.
11. This product is suitable for use in damp locations where the ambient temperature is 0°C minimum, +55°C maximum. Product is also suitable for installation in sealed and gasketed fixtures, Product is not suitable for heated air outlets and wet or hazardous location. Maximum allowable case temperature is 65°C. See page 4 for measurement location.
12. To avoid electrical shock, please disconnect normal and emergency power supplies, and battery connector of the emergency driver before servicing.

13. This emergency driver is for factory or field installation inside, on top of, or remote from the fixture depending on model configuration.
14. For Canadian application the output terminals should be in compliance with the accessibility requirement of the Canadian electric Code.
15. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference that may cause undesired operation.
16. This product's chassis must be grounded.
17. Unswitched AC power source of 120 VAC through 277 VAC is required.
18. The battery is sealed, non-maintenance, and is not replaceable in the field. Please contact manufacturer for information on service. Do not attempt to service the battery.
19. Install in accordance with National Electric Code and local regulatory agency requirements. Installation is to be performed only by qualified personnel.
20. DO NOT EXCEED TOTAL OUTPUT RATING of source power equipment.



Ni - Cd

**THIS PRODUCT CONTAINS A RECHARGEABLE NICKEL-CADMIUM BATTERY. THE BATTERY MUST BE RECYCLED OR DISPOSED OF PROPERLY.**

# Installation Instructions for the Sure-Lites LED Emergency Driver



**CAUTION: DO NOT JOIN CONVERTER CONNECTOR UNTIL INSTALLATION IS COMPLETE AND AC POWER IS SUPPLIED TO THE EMERGENCY DRIVER.**

**NOTE:** Make sure the necessary branch circuit wiring is available. An unswitched source of power is required. The emergency driver must be fed from the same branch circuit as the AC driver.

This product is suitable for field installation with suitable LED loads including LED luminaires, DC voltage driven LED replacements for fluorescent lamps and others. There are 4 checks to determine if your luminaire is eligible for field installation.

1. Ensure the LED load's rated power is greater than or equal to the power output of this emergency LED driver. This is to ensure that this emergency product will not produce more power than the LED load can handle, thus ensuring that the LED load will not be damaged when the system is in the emergency mode.
2. Verify that the forward voltage of the luminaire's LED array is within the limits of this emergency LED driver. The forward voltage of the LED array is commonly designated as Vf and should be found on the luminaire markings, in the luminaire specifications, or imprinted directly on the LED arrays. If multiple LED arrays are to be driven, verify that the total forward voltage is within the limits of this product. Using a voltage meter, it may be possible to directly measure the voltage across the LED arrays when operating from the AC driver.
3. Ensure the output current of the LED driver does not exceed 3.0 Amps. This is the current into the blue wire.
4. Ensure there will be sufficient light output in the end application. Estimate the egress lighting illumination levels by doing the following:
  - a. Find the efficacy of the LED load. This can be given by the luminaire manufacturer. This number will be given in lumens per watt (lm/w). It is the installer's responsibility to validate the luminaire manufacturer's efficacy data. This can be accomplished by direct measurement, by review of independent 3rd party test data (UL, ETL, etc.), accessing a public database of 3rd party data (such as Design Lights Consortium, www.designlights.org), or other comparable means.
  - b. Lumens can be calculated by multiplying the output power of the emergency LED driver by the efficacy of the LED load. In many cases the actual lumen output in emergency mode will be greater than this calculation gives, however it will provide a good estimate for beginning the lighting design of the system.
  - c. Using the results of this calculation and industry standard lighting design tools, calculate the anticipated illumination levels in the path of egress.

**Lumens In Emergency Mode = Lumens per Watt of**

**Fixture \* Output Power of Chosen Product**


$$\text{(Lumens)} = \text{(lm/W)} * \text{7.5(W)}$$

**NOTE:** This product has been designed to reliably interface with a wide selection of LED loads and is electrically compatible with every simple LED array that meets criteria 1 and 2 above. However, compatibility cannot be guaranteed with all current and future LED systems. Compatibility testing of the end-use system is suggested. Please contact the factory with any questions.



## INSTALLING THE EMERGENCY DRIVER

1. Disconnect AC power from the LED luminaire.
2. Mount the emergency LED driver by the mounting tabs using the supplied screws. The luminaire's installation instructions may provide guidance on the recommended mounting location.
  - > **Mounting Height:** This product meets or exceeds the NFPA minimum light requirements with all loads, down to the smallest rated lamp load, at heights up to 7.17ft (2.2m). Many factors influence emergency illumination levels, such as the lamp load selected, luminaire design, and environmental factors therefore end use verification is necessary. For field installations, when the attached luminaire is mounted at heights greater than 7.17ft (2.2m), the level of illumination must be measured in the end application to ensure the requirements of NFPA 101 and local codes are satisfied.
  - > **Remote Mounting:** The emergency driver may be remote mounted from the luminaire. If used in conjunction with an AC driver, this distance is up to half the distance the AC driver manufacturer recommends remote mounting the AC driver from the LED Load. If used without an AC driver, consult factory. The test button indicator light may also be remote mounted. **CAUTION:** Remote mounting can result in reduced power output. For remote mounting more than five feet from the luminaire, please consult factory to determine the minimum necessary wire gauge.
3. Mount the supplied test button indicator light in a location that is visible and accessible by maintenance personnel. The test button indicator light mounts through a 1/2" hole which may need to be made in the luminaire or could come pre-punched by the luminaire supplier.
4. Wire the test switch per wiring diagrams provided on these instructions.
5. If wired correctly, the test button indicator light indicator light should be ON when AC power is supplied to the fixture, and the converter connector is closed indicating that the emergency driver battery is charging. After installing, mark with the "PUSH TO TEST" and "CHARGING INDICATOR LIGHT" labels.



# Installation Instructions for the Sure-Lites LED Emergency Driver

6. Select the appropriate wiring diagram to connect the emergency driver to the AC driver and LED load. Make sure all connections are in accordance with the National Electrical Code and any local regulations.
7. After installation is complete, supply AC power to the emergency driver and join the on converter connector.
  - > At this point, power should be connected to both the AC driver and the emergency driver, and the test button indicator light should illuminate indicating the battery is charging.
  - > A short-term discharge test may be conducted after the emergency driver has been charged for one hour. Charge for 24 hours before conducting a long-term discharge test. Refer to OPERATION.
8. In a readily visible location, attach the label "**CAUTION - This Unit Has More Than One Power Connection Point. To Reduce The Risk Of Electric Shock, Disconnect Both The Branch Circuit-Breakers Or Fuses And Emergency Power Supplies Before Servicing.**"

**NOTE:** After installation, it will be necessary to measure the egress lighting illumination levels to ensure it complies with national, state, and local code requirements.

## MAINTENANCE

This self-testing emergency driver automatically performs required routine testing. Results are reported to maintenance personnel via the indicator light.

**Note:** Maintenance personnel should periodically check the indicator light. If the test button indicator light is flashing, follow steps in the *Troubleshooting Guide*.

Failure Status will be reset when the unit passes:

- The next automatic test, or
- An actual power failure exceeding 10 seconds.

## SELF-TESTING OPERATION

This unit contains a control/monitor circuit that automatically performs a 30-second discharge test once a month and a full 90-minute discharge test once a year. During routine testing, the self-testing emergency driver simulates an AC power failure causing the unit to automatically switch to emergency mode. The unit will monitor the operation of the LED load, battery voltage, LED load connections and emergency duration. If the emergency system functions properly, then the unit will return to normal mode. Should the unit detect any problems, the test button indicator light will flash per failure condition (see Troubleshooting Guide) until the condition has been corrected and the unit passes the next test. To reset a failure indication turn off AC power to the emergency driver for a minimum of 10 seconds, or briefly push the test button indicator light. If the condition has not been corrected by the next scheduled test, the unit will once again detect the failure and signal the failure indicator.


## OPERATION

During normal operation, AC power is applied and the self-testing emergency driver charges the battery. Connecting the (red and white) converter connector wires enables the emergency circuit and supplies power to the control/monitor circuit and charging indicator light. The self-testing emergency drive continually monitors the unit health. Should the unit detect an unusual condition, the test button indicator light will flash. When AC power fails, the self-testing emergency driver automatically switches to emergency mode, keeping the LED load illuminated at a reduced lumen output for a minimum of 90 minutes. When AC power is restored, the self-testing emergency driver returns to charging mode.

TROUBLESHOOTING GUIDE		
STATUS INDICATOR LIGHT	PROBLEM	CORRECTIVE ACTION
Light on, not flashing	None	None. Unit is Operating Correctly.
Flashing 2 times every 5 seconds	Battery Error	Charge battery. If after an hour failure is still indicated, see action below.
Flashing 3 times every 5 seconds	Charging Error	Ensure input wiring is correct and verify voltage is correct and stable. (WHITE, BLACK wires)
Flashing 4 times every 5 seconds	Output Error	<ol style="list-style-type: none"> <li>1. Output might be either open or short circuited.</li> <li>2. Ensure that fixture wiring is in accordance with proper wiring diagram.</li> <li>3. Ensure connections of Yellow and Yellow Black wires.</li> </ol>
Continuous Flashing	Application out of range	Ensure LED load is operational and specified for self-testing emergency driver



**NOTE:** The unit engage connector (red and white wires) must be connected for the AC driver to operate normally.

# TCASE TEST POINT LOCATION



## WIRING DIAGRAMS

**EMERGENCY DRIVER AND AC DRIVER MUST BE FED FROM THE SAME BRANCH CIRCUIT.**  
 TYPICAL SCHEMATICS ONLY. MAY BE USED WITH OTHER DRIVERS. CONSULT THE FACTORY FOR OTHER WIRING DIAGRAMS.



**MAY BE USED WITH OTHER DRIVERS**

**Cooper Lighting Solutions**  
 1121 Highway 74 South  
 Peachtree City, GA 30269  
 P: 770-486-4800  
[www.cooperlighting.com](http://www.cooperlighting.com)

© 2020 Cooper Lighting Solutions  
 All Rights Reserved  
 Tous droits réservés  
 Todos los derechos reservados

Printed in USA  
 Imprimé aux États-Unis  
 Impreso en los EE. UU.  
 Publication No. IB505080EN  
 08/10/2020 442295193011

Cooper Lighting Solutions is a registered trademark. All trademarks are property of their respective owners.

Cooper Lighting Solutions est une marque de commerce déposée. Toutes les autres marques de commerce sont la propriété de leur propriétaire respectif.

Cooper Lighting Solutions es una marca comercial registrada. Todas las marcas comerciales son propiedad de sus respectivos propietarios.

Product availability, specifications, and compliances are subject to change without notice.

La disponibilité du produit, les spécifications et les conformités peuvent être modifiées sans préavis.

La disponibilidad de productos, las especificaciones y los cumplimientos están sujetos a cambio sin previo aviso.

