

Transceiver Module TM751

INSTALLATION AND OPERATING INSTRUCTIONS

The TM751 Transceiver receives commands from X10 Remote controls and turns on a light or appliance connected to its outlet. The Transceiver also passes the signals onto your house wiring to control lights, appliances, or Wireless Cameras around your home. You plug lights and appliances into X10 Modules (sold separately). You plug Wireless Cameras into Addressable Power Supplies (sold separately).

1. Plug the TM751 Transceiver into any 120V AC outlet. Fully extend its antenna.
2. Use a dime to set the Housecode dial on the TM751 to match the X10 modules, cameras, and remote controls you will be using it with.
3. Plug a lamp or appliance into the outlet on the TM751 (observe the ratings on the back of the TM751).
4. Press the small button on the TM751 to test that the lamp/appliance goes on and off.
5. Install 4 AAA alkaline batteries in an HR12A PalmPad remote control, or CR12A ScanCam remote control (each sold separately).
6. Press 1 ON and OFF on the remote control to control the light/appliance connected to the TM751.
7. Press the corresponding ON or OFF button on the remote control to turn other X10 Modules or cameras on/off.

Also see instructions included with X10 remote controls and cameras.

**For help or more information on setup, please visit
www.x10.com/support**

Trim

FCC CAUTION: THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES. OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITIONS: (1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND (2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED, INCLUDING INTERFERENCE THAT MAY CAUSE UNDESIRE OPERATION.

This equipment generates and uses radio frequency energy, and if not installed and used properly, that is, in strict accordance with the manufacturers instructions, it may cause interference to radio and television reception. It has been type tested and found to comply with the limits for remote control devices in accordance with the specifications in Sub-Parts B and C of Part 15 of FCC Rules, which are designed to provide reasonable protection against such interference in a residential installation. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause interference to radio or television reception, which can be determined by unplugging the equipment, try to correct the interference by one or more of the following measures.

- Reorient the antenna of the radio/TV experiencing the interference.
- Relocate the product with respect to the radio/TV.
- Move the product away from the radio/TV.
- Plug product into an outlet on a different circuit from the radio/TV experiencing the interference.
- If necessary, consult your local Dealer for additional suggestions.

***NOTE:** Modifications to any of the components in this kit will void the user's authority to operate this equipment.*

X10 Wireless Technology, Inc. 90 Day Limited Warranty

X10.com, a division of X10 Wireless Technology, Inc. (X10) warrants X10 products to be free from defective material and workmanship for a period of 90 days from the original date of purchase at retail. X10 agrees to repair or replace, at it's sole discretion, a defective X10 product if returned to X10 within the warranty period and with proof of purchase.

If service is required under this warranty:

1. Visit www.x10.com/support/return_policy.htm, or e-mail sales@x10.com to obtain a Return Merchandise Authorization (RMA) number.
2. Return the defective unit postage prepaid to X10 (see address on back).
3. Enclose a check for \$4.00 to cover postage and handling.
4. Enclose a dated proof of purchase.
5. X10 is not responsible for shipping damage. Units to be returned should be packed carefully.

Please visit www.x10.com/support for help.

TM751-6/13

Trim

Print reduced by approx 85%.

Final size of above = approx. 7 3/4" x 4 3/4"

Folds into a sheet 3 7/8" x 2 3/8"

(Like all other instruction sheets)

X10 Wireless Technology, Inc.
400 Forge Way, Suite 409-412,
Rockaway, NJ 07866

RMA#

Tear off and keep the portion to the right (setup instructions are on the other side of it) and keep for future use.

visit www.x10.com/support/return_policy.htm
or e-mail sales@x10.com to obtain a Return Merchandise
Authorization (RMA) number.

Write your RMA number above. Tear off and tape this label to
the outside of the package and mail it (postage prepaid).

Trim

Mini Timer MT13A

A Controller, Timer and Alarm Clock all in one! Programs up to eight X10 Modules to go on and off at specific times, up to a total of 64 timed events. Controls eight modules instantly. Dims lights too.

Maxi Controller SC503

Lets you control up to 16 X10 Modules at the touch of a button from anywhere in the house. Dims lights too!

Mini Controller MC10A

Lets you control up to eight X10 Modules at the touch of a button from anywhere in the house. Dims lights too!

2-Way Home Control Interface CM15A

Set up from a PC to control up to 256 X10 Modules. ActiveHome Pro software download & USB cable included.

Thermostat Set-Back TH2807

Automatically sets-back your central heating/air conditioning. Mounts on the wall under your existing thermostat and plugs into an Appliance Module.

Wireless Remote Control System RC5000

Lets you control 16 X10 modules from inside or outside your home. Can also dim and brighten Lamp Modules and Wall Switch Modules. Works with the HR12A PalmPad Remote and X10 RF Wall Switches (SS13A, SS15A).

Lamp Module LM465

Can be Dimmed and Brightened from any X10 Controller. Responds to "All lights on". Rated for 300 W. Incandescent only.

2-Way version LM14A.

SocketRocket LM15A

Screws in to an existing light fixture. Controls up to 150W, incandescent only.

Appliance Module - AM486/AM466

Two pin polarized (AM486) or 3 pin grounded (AM466). For controlling an air conditioner, TV, stereo, etc. anywhere in the home. Rated 15A for heaters, coffee pots etc.; 1/3 H.P. for motors; 400W for TVs; 500W for lamps. *2-Way versions available AM14A (2 pin), AM15A (3 pin).*

Wall Switch Module WS467

For controlling important indoor and outdoor security lights. Replaces your existing wall switch and installs like a regular dimmer. Dimmed/brightened from any X10 Controller. Rated 500W incandescent only.

3 - Way Wall Switch Module WS4777

For controlling a light which is controlled by two switches. Same features as WS467.

Split Receptacle Module SR227

Replaces existing wall outlet. The top outlet functions like an Appliance Module, the bottom one is a regular outlet. Rated 15A.

Universal Module UM506

Isolated contact relay and beeper. Can be set for momentary or continuous operation. Not compatible with X10 security systems.

Trim