

600E Series

Steel Direct View LED Exit

The 600E Series is the brightest most visible sign in the industry in both normal and smoke-filled environments. Constructed of durable 20 gauge steel, this direct view exit provides bright illumination with individual LEDs spelling the word EXIT, includes a decorative steel frame on face.

FEATURES

- Enclosure constructed of rugged 20 gauge steel
- Solid 1/8" thick, vandal-resistant, polycarbonate lens
- Low voltage disconnect eliminates deep discharge
- Brown-out, short circuit and voltage surge protection
- Overcharge protection
- Combination exit/ emergency light option available (REN2)
- Flasher (FL) options to meet ADA regulations
- 8w remote capability (ELO) or REN2 Combo options available
- Maintenance-free NiMH (standard) and SLA (EL/ REN2/G1) batteries
- Ceiling, wall or end mount
- Constant, uniform illumination by long-life, high intensity, red or green LEDs
- Optional Guardian Self-Diagnostics (G1) available
- Field selectable directional chevrons
- 120/277V dual primary, 50/60Hz input
- Standard finishes: Black, White or Brushed Chrome
- Assembled in U.S.A.

WARRANTY

Any component that fails due to manufacturers defect is guaranteed for 25 years with a separate 5 year pro-rated warranty on the battery. The warranty does not cover physical damage, abuse or instances of uncontrollable natural forces. See the full Exitronix warranty document for detailed information.

Model: _____ Date: _____
 Accessories: _____
 Job Name: _____ Type: _____



REN2 Option



ORDERING INFORMATION Example: 602E-WB-WH-DR

| Series | Power Source | Finish | Options (Factory Installed) | Combo Option ¹⁰ |
|---|---|---------------------|---|--|
| 602E = Red Single Face | LB = AC Only | WH = White | C6 ¹ = White Face w/Red Letters | EL0 ^{5,6} = 8 Watts Remote Capacity |
| 603E = Red Double Face | WB = NiMH Battery (Std) | BL = Black | C10 ² = White Face w/Green Letters | REN2 ⁵ = (2) Renegade 3.6W PAR36 LED Lamps |
| G602E = Green Single Face | 2C1 ⁹ = 2 Circuit Input 120/120V | BC = Brushed Chrome | DL = Downlight | Accessories¹¹ (Field Installed) |
| G603E = Green Double Face | 2C17 ⁹ = 2 Circuit Input 277/277V | | DR = Damp Location Rated | |
| | 2C117 ⁹ = 2 Circuit Input 120/277V | | FL ³ = Flasher | |
| Notes | | | G1 ³ = Self-Diagnostics | ER1-KIT = 1' Pendant Mount Kit |
| | | | TRH ⁴ = Tamper Resistant Hardware | ER2-KIT = 2' Pendant Mount Kit |
| | ¹ Only available with 602E and 603E | | | REN2XX-MP2 ⁷ = Single REN2 w/ Mounting Plate |
| | ² Only available with G602E and G603E | | | REN2XX-MP2 ⁷ = Double REN2 w/ Mounting Plate |
| | ³ Only available with WB (SLA Battery) | | | REN2XX-WP-MP2 ⁷ = Sgl REN2 w/ Mounting Plate ⁸ |
| | ⁴ Must order Tamper Tool (TRHT-6H-8H) as separate line item | | | REN2XX-WP-MP2 ⁷ = Dbl REN2 w/ Mounting Plate ⁸ |
| | ⁵ Must be ordered with WB and G1 options (cannot be combined with any other options, utilizes a SLA battery) | | | TRHT-6H-8H = Tamper Tool |
| | ⁶ For use with Renegade Remote lamp heads (order remote lamps separately) | | | WG-1 = Wire Guard (Back Mount) |
| | ⁷ XX = BB for Black or WH for White | | | WG-2 = Wire Guard (End Mount) |
| | ⁸ Weatherproof version | | | WG-3 = Wire Guard (Ceiling Mount) |
| ⁹ Not available with G1 option | | | WG-6 = Wire Guard For Combo (Back Mount) | |
| ¹⁰ EXIT LEDs flash in emergency mode when remote or combo option is selected | | | XG-1 = Poly Guard (Back Mount) | |
| | | | XG-3 = Poly Guard (Ceiling Mount) | |

CONSTRUCTION

Our specification grade 600E series enclosure, faceplate, and mounting canopy are 20 gauge galvanized steel with decorative powder coat paint. Faceplate has 3/4" black letters with red or green LEDs. 1/8" polycarbonate shield protects LEDs from impact. Optional faceplates are available.

ILLUMINATION

Illumination of the 600E series is accomplished utilizing high-intensity, long-life LEDs exceeding UL 924 requirements for brightness and uniformity. LEDs provide excellent, even illumination while maximizing energy efficiency. LEDs are a maintenance-free solution, providing up to 100,000 hours of use without failure.

EMERGENCY LIGHTS - (Option: REN2)

Emergency lights feature field-selected top or side mounting. The 600E series is RENEGADE compatible - 3.6W LED PAR36 style head.

ELECTRICAL

Input

Dual-voltage input 120 or 277VAC @ 50/60Hz.

Nickel-metal Hydride - NiMH (Standard)

Exitronix NiMH batteries are maintenance-free with a life expectancy of 15 years. NiMH batteries perform optimally in temperatures ranging from 32°F to 104°F (0°C to 40°C).

Brownout Circuit

Brownout circuit monitors the line voltage, as the line voltage sags and can no longer illuminate the exit sign to meet UL924 visibility test, the emergency circuit will turn on to supply a portion or all the power to illuminate the sign for a minimum of 90mins until the line voltage is restored.

Low Voltage Disconnect

Low Voltage Disconnect (LVD) measures the battery terminal voltage. The LVD continuously monitors the battery terminal voltage and if it should fall below a preset voltage threshold, the LVD will disconnect the load. When the battery is recharging and voltage is raised above another preset voltage threshold, the load is automatically reconnected.

Solid-State Transfer

The circuit features solid-state switching for emergency lamps, eliminating concerns of damaged contact or mechanical failures associated with relays. The switching circuit detects a loss of line voltage and automatically switches to emergency mode.

Overload and Short-Circuit Protection

The overload monitoring system is a solid state circuit which monitors the lamp load and disconnects from the battery shall an overload or short circuit occur. The overload current protection eliminates the need for fuses or circuit breakers for the DC load.

Test Button

The test button is easy to locate and provides manual verification of the transfer circuit and emergency lamps.

INSTALLATION

Installs in minutes with easy-to-read instructions and detailed diagrams. No special hardware or tools necessary. Internally housed components and battery eliminate the use of a canopy when wall mounting single faced exits. Mounting canopy included.

Assembled in the U.S.A. (Standard)

Assembled in the U.S.A. and is in full compliance with the American Recovery and Reinvestment Act of 2009 (ARRA) requirements and Buy American provisions.

OPTIONS

Damp Location Rated (Option: DR)

Damp location rated fixture that is normally or periodically subject to condensation of moisture in, on or adjacent to, and includes partially protected locations.

Remote Capacity (Option: EL0)

8 Watts of Remote Capacity allows for up to (2) Renegade Remote lamp heads to be powered by the 600E series. Must order Renegade lamp head accessories as a separate line item.

Guardian Self-Diagnostics (Option: G1)

The Guardian circuit continuously monitors the operating condition of the battery charging circuit and battery supply voltage. The purpose of this option is to provide visual signaling in response to a fault at the EXIT sign battery and/or battery charger. If a failure is detected, visual status will occur immediately via the CHARGER LED and/or the BATTERY FAULT LED. The LEDs will stay illuminated until the fault is corrected.

Flasher (Option: FL)

When normal power is lost and the emergency unit goes into back up power mode, this unit will flash on and off - providing a highly visual signal as to emergency status.

CONFORMANCE TO CODES & STANDARDS

The 600E Series meets or exceeds the following: UL 924, NEC requirements and NFPA 101.

DIMENSIONS

