

## CITYLINE PROXIMITY READER



**Reference:** 06992

- \* Reader that allows the door to be opened when a remote key fob or card is used. Only authorised cards or key fobs will activate the device. Physical contact is not necessary.
- \* Proximity reader that...

### DESCRIPTION

- \* Reader that allows the door to be opened when a remote key fob or card is used. Only authorised cards or key fobs will activate the device. Physical contact is not necessary.
- \* Proximity reader that uses an incorporated dipswitch configuration (SW2) and can function with an autonomous or centralised system.

AUTONOMOUS configuration.

- \* Capacity for up to 400 user cards or key fobs.
- \* Reader and controller integrated into the same module.

Configuration as a CENTRALISED MDS-AC Plus.

- \* Proximity reader with capacity for up to:
  - 1020 user cards/key fobs with the central MDS unit (ref. 2405).
  - 2048 user cards/key fobs with the central AC Plus unit (ref. 4410).
- \* Reader and controller integrated into the same module.

CENTRALISED configuration with the Wiegand 26 or Data/Clock protocols.

- \* When the reader starts in the following modes:
  - Wiegand-26, the + LED will light for one second.
  - Data/Clock, the - LED will light for one second.
- \* Proximity reader with capacity for up to:
  - 1020 user cards/key fobs with the central MDS unit (ref. 2405).
  - 2048 user cards/key fobs with the central AC Plus unit (ref. 4410).
- \* Requires the door controller (ref. 4420) for connection and functioning.
- \* Acoustic and visual confirmation via LEDs which indicate whether the presented card has been accepted or rejected.
- \* Integrated into an aluminium plate.
- \* Either embedded (ref. 8948, including box) or surface mounted (ref. 7061, optional).
- \* Recommended for indoor and outdoor use.

### TECHNICAL SPECIFICATIONS

AUTONOMOUS Technical Characteristics:

- Does not require physical reader-card contact. 5 cm (card) or 1.5 cm (key fob) reading distance.
- Acoustic and visual information for operations.
- Simple programming - either manually or by PC (registering-unregistering cards).

- Door control sensor and exit button.
- Exit relay.
- Lock-release activation by relay with programmable times. Programmable for 1 to 99 seconds.
- Signalling LEDs (programming assistance and status).

#### Autonomous Programming

- Can be carried out in 3 ways:
  - Using a master card.
  - Private programming keyboard.
  - PC software.

#### CENTRALISED MDS-CAC Technical Characteristics:

- Does not require physical reader-card contact. 5 cm (card) or 1.5 cm (key fob) reading distance.
- Acoustic and visual information for operations.
- Lock-release button entry, door sensor entry and lock-release relay (C, NO, NC, volt-free).
- Reader cables – Central Unit: 2 wire (power supply) + shielded twisted pair (data). For installations with several readers these may be connected in cascade.
- Has a dipswitch (SW1) in order to configure:
  - Door number (switches 1 to 5): the access number/door (0 to 31).
  - Switch 6: No function.
  - Lock-release (switches 7 to 8): depending on the installation:
    - Lock-Release Opening Time (seconds) in MDS.
    - In CAC, configuration via software (switches not used).
- CN3 Connector: Keyboard connector.
- The lock-releases can be directly connected to the reader and the relay decoder used for maximum security installations.

#### Centralised Programming

Programming carried out using the PC software for the installed central unit (ref. 2405 or ref. 4410).

#### CENTRALISED Technical Characteristics with the Wiegand 26 or Data/Clock protocols:

- Does not require physical reader-card contact. 5 cm (card) or 1.5 cm (key fob) reading distance.
- Acoustic and visual information for operations.
- The Wiegand (WG) or Data/Clock readers provide the installation with greater protection from possible sabotage, as neither the reader nor the exit button connection are connected to the door opening mechanism. All of the devices are connected to the door controller and as such cannot be interfered with. The door controller is installed in the interior (safe area) and the reader installed outside.
- The reader may be used with other door controllers that use the Wiegand 26 (WG) or Data/Clock protocols.
- Cabling: 7 wires to the door controller.
- For more information see the Technical Characteristics of the door controller.

#### Centralised Programming

Programming carried out using PC software for the corresponding installed central unit (ref. 2405 or ref. 4410).

#### Specifications

Dimensions (HxV mm): 130 x 128

Flush mounted box (HxVxP mm - included): 115 x 114 x 45

Surface box (HxVxP mm - optional): 130 x 128 x 33

Environmental protection (IP): 52

Impact protection (IK): 07

Power supply (V):

Autonomous: 12V (ac/dc).

Centralised: 12Vdc Consumption (mA) without lock-release: 90

Operating temperature: -15 to 55°C

**Weight:** 0,583201 kg

**Size of product when packed:** 15x13,8x7 cm

**EAN 13:** 8424299069920



U1, 37-39 Green St,  
Banksmeadow, NSW. 2019  
p. 61 2 9700 1700  
f. 61 2 9700 1955  
sales@fermaxaus.com.au



U11, 8 Fortitude Cres,  
Burleigh Heads, QLD. 4220  
p. 61 7 5520 2266  
f. 61 7 5520 4591  
qld@fermaxaus.com.au



U30, 640-680 Geelong Rd,  
Brooklyn, VIC. 3012  
p. 61 3 9314 2220  
f. 61 3 9314 7772  
vic@fermaxaus.com.au



PO Box 587  
Balcatta. 6914  
m. 0438 700 101  
wa@fermaxaus.com.au