

LED UNDER CABINET

INSTALL INSTRUCTIONS

PLEASE FIND A QUALIFIED ELECTRICIAN FOR INSTALLATION. Please read the instructions before you install and use the luminaire.

These Portable Luminaries have a polarized plug (one blade is wider than the other) as a safety feature to reduce the risk of electric shock. This plug will fit in a polarized outlet only in one way; if the plug does not fit fully in to the outlet, reverse the plug. If it still does not fit, contact a licensed electrician. Never use with an extension cord unless the plug can be fully inserted. Do not alter the plug.


- Use only insulated staples or plastic ties to secure cord.
- If used as an under cabinet light, route and secure cords so that they will not be pinched or damaged when the cabinet is pushed to the wall.
- Position the portable under cabinet light so that the lamp replacement markings are clearly visible during re-lamping.
- Installation only intended for under cabinet, under shelf, or cove applications.
- Not intended for surface or recessed installation inside built-in furnishings such as; kitchen cabinets, china cabinets, or trophy cases.
- The National Electrical Code (NEC) does not permit cords to be concealed where damage to the insulation may go unnoticed. To prevent fire danger, do not run cords behind walls, ceilings, soffits, or cabinets where it may be inaccessible for examination. Cords should be visually examined periodically and immediately replaced when any damage is noted.
- The portable Cabinet Luminaries may be installed inside a kitchen cabinet or other built-in furnishing provided that the cabinet or built-in furnishing is provided with a dedicated receptacle and the line voltage cord is not concealed or routed through openings in the cabinet or furnishing.
- There are no user serviceable parts inside light. Do not open fixture or damage may result and will void warranty.
- The LEDs on this fixture are not user serviceable. The LEDs strip cannot be replaced.

Interconnection of fixtures must remain within the current rating and the maximum number of units in accordance with the table below:

WATTS	VOLT	CURRENT	MAX. INTERCONNECTED LAMPS
8	120V	0.08A	15
12	120V	0.12A	12
14	120V	0.14A	10




WARNING DISCONNECT POWER BEFORE INSTALLING OR SERVICING.




1. INSTALL THE CLAMPS

Choose an appropriate position on cabinet, counter or wall and anchor the 2 clamps in a suitable distance with included screws.




2. PUSH LAMP CAREFULLY INTO CLAMPS

The brackets should be secure the lamp could fall down causing damage.



3. WIRING

Insert cord into the pins and connect plug to the socket. Turn power back on.



4. Multiple units can be electrically interconnected using supplied Direct Connector or optional Connecting Cables.

OPERATION & MAINTENANCE

- Turn on the power supply, ensure the light works normally without flashing.
- Opening the lamp may cause damage.
- Average lamp life may lengthen when operated at lower temperatures.
- Non-dimmable switches are recommended.
- Shut off or disconnect power before servicing or replacing.

CLEANING: Use a dry cloth to wipe off any smudges on the lamp.