

Item#: 09355 LED EMERGENCY PACK SPLIT TYPE/L

FEATURES

- Programmable constant current driver
- SELV for output voltage <60V DC
- Open and Short Circuit Protection
- No PCB
- Sound Rated A
- Class 2

APPLICATION

For use with drivers that are 100W or less that are in LED fixtures.

INPIIT

INPUT		
Input Current	100mA Max.	
Input Voltage	120-277V 50/60hz	
Power Factor	0.6	
OUTPUT		
Output Power	8W Max.	
Output Current	100-1050mA	
Output Voltage	11-56V	
Output Short Protection	Yes	
Output Open Protection	Yes	
PERFORMANCE		
Recharge Power	8W Max.	
Standby Power	<0.5W	
Red Lead	3A, 90V	
White/Black Lead	100W Max.	
Time to Light	0.3S from detection of	
	emergency event	
Recharge Time Required	24 Hours Max.	
Battery Type	LiFePO4 9.6VDC	

ENVIRONMENT

Battery Capacity Available

Ambient Temperature	50° ~ 122°F
Tc MAX	158°F / 70°C

LIFESPAN

Warranty (Years)	5
------------------	---

QUALIFICATIONS





 $\textit{UL / UL R/C, Class 2} \cdot \textit{FCC Part 15 Class B} \cdot \textit{Specifications are subject to change without notice}.$


1500mAh

Item#: 09355 LED EMERGENCY PACK

DIMENSIONS (Inches)	DRIVER	BATTERY
Length	5.9"	8.1"
Width	1.7"	1.1"
Height	1"	0.84"
Weight (Lbs)		







PACKAGING		UPC	DIMENSIONS (LxWxH)	GROSS WEIGHT (Lbs)
Master Carton	10	10811768024293	16.1" x 7.2" x 10.6"	17.4
Individual Box	1	811768024296		1.7
Country of Origin	China			
HS Tariff	9405.99.4090			

ORDERING

ITEM#	DESCRIPTION	TITLE 20	CASE
09355	EMERGENCY PACK FOR LED FIXTURE 8W/90 MIN - SPLIT TYPE/L	Yes	10

ADDITIONAL INFORMATION:

- For use with drivers that are 100W or less that are in LED fixtures.
- An un-switched AC power source of 120V AC to 277V AC is required.
- This device is designed for use in fixtures listed for dry and damp locations.