

# 4" RETROFIT SELECTABLE WHITE LED LIGHT

Smooth/Baffle

Install Guide and Manual

## COMPONENTS




TP24 Connector



E26 Base




## EASY INSTALLATION



**1. Turn off the circuit breaker that provides power to the light switch for the recessed lights.**

**2. Locate the recessed housing.**  
 • Remove previous fixture. Fixture may be hot so allow time to cool after turning off power.

**3. Ensure the size of the opening is 4"**




TP24 Connector

E26 Base

**Required Tools:** Ladder, Drywall Saw, Wire Strippers

**4. Determine the type of power connector available in your recessed can housing.**

- TP24 Connector
- E26 Socket



**5. Connect the appropriate adapter (E26 or TP24) to pull power from the housing.**


**NOTE:** The wires may come lose from the connectors. Ensure they are attached.

**6. Turn on power and test light.**



**7. BEFORE PROCEEDING:** On back of retrofit fixture, slide the CCT Selection Switch to choose from five color temperatures (2700K, 3000K, 3500K, 4000K, 5000K). Try each CCT to determine best fit.

- Light will use the preferred setting whenever you turn it on.
- Turn off light switch after selecting your choice and continue install.



**8. Tuck all wires into the can.**

**9. Line up trim ring with opening.**

**10. Push downlight into can until secure. Compressions clips will hold retrofit light in place.**



Turn Power ON

**11. Turn on circuit breaker and test light.**

## WARNING

To reduce the risk of fire, electric shock or injury to people:

- This product should be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.
- Abide by related regional and local laws or regulations.
- Do not alter, relocate or remove wiring.
- Do not make or alter any open holes in enclosure or electrical components.
- Proper grounding is required to ensure safety.
- Check for damage during shipping prior to install. If the product is damaged, do not use it.
- Turn off the switch and circuit breaker before installing this LED light.
- Use safety precautions. Safety eyeglasses and gloves are recommended.
- Please review instructions carefully before proceeding.

## SPECIFICATIONS

Voltage	120V
Wattage	11W
Suitable for Locations Ingress	Damp
Housing	Aluminum+PC
Weight	0.33-0.34lbs
Warranty	7 years