



G25 FILAMENT LED BULB

Dimmer Compatibility Guide

Sunco Lighting Inc. ("Sunco") compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Brand	Model		Brand	Model	
ADORNE	ADPD453LW2	✗	LEGRAND	HCL453PTC	✓
	ADTP703TUW4	✗		HCL453PW	✗
	ADWR703HW4	✗		RHCL453PW	✓
AH	SDM/600/WHTTE 600W	✓	LEVITON	06674-002-10W	✗
	SDM3/1000/WHTTE 1000W	✗		600W 120VAC 60HZ	✗
ALMOND	LUXDM600-12 600W	✓		603-6631-A 600W	✓
APOLLO	SP-521 E184279-C	✗		6631-A 600W	✓
	CJUL-1D-300A	✗		6631-LA 600W	✓
CONFORTO	COMODIDADE DLE-01	✗		6631-LA 600W	✓
COOPER	AAL06-C1	✗		6681	✓
	AAL06-C2-K	✗		6683-10Z 600W	✓
	DAL06P-C2-K	✗		6683-IW 600W	✗
	SAL06D-PTA	✗		6684 600W	✓
	SAL06P-W-K	✗		DDE06-BLZ 600W	✓
	TAL06P-C2-K	✗		DDL06 600W INC	✗
CRUS	E236731 120V-60HZ 100W	✗		DDL06-001-1LZ	✓
CTL	DM600-12-3/LED/WH 600W	✓		DDL06-010-BLZ	✓
EATON	AAL06-C1	✗		DDMX1-011-BLZ	✓
	SAL06P3	✗		DSE06-001-10Z	✓
	TAL06P1-C5	✗		DSL06-001-1LZ	✓
GE	18024 600W	✗		DW6HD-1BZ DECORA SMART	✓
GEN	2.0 AC CONTROL 120VAC 60HZ	✗		IPE04-1LZ 400VA	✗
	2.0 DC CONTROL 120VAC 60HZ	✗		IPI06 600W	✓
	1.9 CONTROL 120VAC 60HZ	✗		IPI06-1LZ 600W	✓
GLOBAL	CONTROL 100-240VAC 50/60HZ	✗		IPL06-011-10Z	✓
HALO	SAL06P-W-HALOGF2	✗		LIGHT ALMOND NO.6672 600W	✓

Continued...

We highly recommend using an LED dimmer that is also an ELV (electronic low voltage) dimmer. A buzzing or flickering light is typically an indication that the dimmer being used is not compatible with the lights. Please consult dimmer manufacturer for maximum lamps per dimmer capacity.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.



G25 FILAMENT LED BULB

Dimmer Compatibility Guide

Sunco Lighting Inc. ("Sunco") compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Brand	Model		Brand	Model	
LEVITON	LIGHT ALMOND NO.6681 600W	✓	LUTRON	CT-600PR-WH 600W	✓
	NO.6681 600W	✗		CTCL-153PDH-WH	✗
	NO.6683 600W	✗		CTCL-153P-WH 600W	✗
	RDL06-001-10Z	✓		D-600PH-3CK 600W	✗
	S-600P-WH	✓		D-600PH-DK 600W	✓
	SLIDE DIMMER	✗		D-600RH-DK 600W	✓
	SLIDE DIMMER 3WAY	✗		D-600R-IV 600W	✓
	SLIDE DIMMER NO.6672	✗		D-600R-WH 600W	✓
	SLIDE DIMMER NO.6674	✗		DIVA CL	✗
	SLIDE DIMMER SURESLIDE	✗		DIVA C-L	✗
	SLIDE NO.IPL06 R50-IPL06-10M	✗		DIVA DVELV-300P-WH	✗
	TSM10-012-1LW	✗		DV-600PH-WH 600W	✓
	WHITE NO.6631 600W	✓		DV-600P-WH	✓
	WHITE NO.6674 600W	✓		DV-603P 600W	✓
	WHITE NO.IPL06 600W	✓		DV-603PH-WH 600W	✓
	IPI10-1LZ 600W	✗		DV-603PH-WH 600W	✓
LINTERTEK	K243111000 120V 60HZ 300W	✗		DV-603PR 600W	✓
	LUSDM600-15L	✗		DVCL-153PH 600W	✓
LUTRON	AY-600PH-WH	✓		DVCL-153PR-WH	✗
	AY-600P-WH	✓		DVCL-153P-WH	✓
	AYCL-153PH	✓		DVCL-153P-WH-3	✓
	AYCL-153P-WH	✓		DVCL-253PH	✓
	CASETA WIRELESS	✗		DVELV-300P-WH 300W	✗
	CL DIMMER TOGGLER	✗		DVELV-303P-WH	✓
	CLEAR CONNECT WIRELESS	✗		DVW-600PH-WH 600W	✓
	CT-103P-WH 1000W	✓		DVWCL-153PH-WH 600W	✓

Continued...

We highly recommend using an LED dimmer that is also an ELV (electronic low voltage) dimmer. A buzzing or flickering light is typically an indication that the dimmer being used is not compatible with the lights. Please consult dimmer manufacturer for maximum lamps per dimmer capacity.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.



G25 FILAMENT LED BULB

Dimmer Compatibility Guide

Sunco Lighting Inc. ("Sunco") compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Brand	Model		Brand	Model	
LUTRON	DVWCL-153PH-WHC	✓	LUTRON	S-600-IV 600W	✓
	LECL-153PH-WH	✓		S-600PR-WH 600W	✓
	LGCL-153CL 600W	✗		S-600P-WH	✓
	MACL-153MH-WH	✓		S-603PGH-WH 600W	✗
	MACL-153MLH-WH	✓		S-603PH-WH 600W	✓
	MACL-153MLRHW-WH	✓		SCL-153PH-WH	✓
	MACL-153MR-WH	✗		SCL-153PH-WH	✓
	MACL-153M-WH	✓		SCL-153P-WH 600W	✓
	MAELV-600-WH	✓		SELV-300P-WH	✗
	MAESTRO	✗		SKYLARK 600W	✗
	MAESTRO MRF2S-6ND-120-SW	✗		SKYLARK SLV-600P-WH	✗
	MAESTRO WIFI MRF2S-6ND-120-WH	✗		TG-600PH-IV 600W	✓
	MA-RH	✗		TG-600PH-WH 600W	✓
	MAW-600 600W	✗		TG-600PNLH-WH	✓
	MAW-600H-AL 600W	✗		TG-603PGH-WH	✗
	MAW-600H-WH 600W	✗		TGCL-153PH-WH	✓
	MIR-600THW-WH	✗		TGCL-153PH-WH 600W	✓
	MRF2-6CL-WH	✗		TGCL-153PLH-WH 600W	✗
	MSCL-OP153MH-WH	✓		PKG1W-WH	✓
	NLV-1000-LA	✗	MARTIN	JERRY MJ-SD01	✗
	PD-6WCL-WH-P	✗	RHINE	UC7067RYE	✗
	P-PKG1W-WH-R	✗	SMART	DIMMER MASTER 300W	✗
	RADIORA2 RRD-6CL-WH	✗	TAANCIL	DIM-L13B	✗
	S-10PH 1000W	✗	TP-LINK	KASA SMART HS220	✗
	S-600 600W	✓	WATTSTOPPER	MICO DETECTOR DCD267-W	✗
	S-600-AL 600W	✓	WEMO	F7C059	✓
	S-600H-WH 600W	✓			

We highly recommend using an LED dimmer that is also an ELV (electronic low voltage) dimmer. A buzzing or flickering light is typically an indication that the dimmer being used is not compatible with the lights. Please consult dimmer manufacturer for maximum lamps per dimmer capacity.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.