Remote Control Instruction

Indicator Light

ON/OFF   Motion Sensor ON/OFF

Short press ON/OFF button to turn on or
off the light
Motion Sensor:
Long press Motion Sensor button
Indicator light blinks once for detection on
Blinks twice for detection off

Motion Sensor

Distance
50%: For detection distance of about 1-3M
100%: For detection distance of about 3-6M

Distance		Brightness	
50%	100%	−	+

Brightness:
-: To lower the level of brightness of the light
+: To increase the level of brightness of the light

Time Untill Standby
30Sec/1Min/3Min/10Min

Standby Brightness

Off	10%	20%	30%

Standby Brightness
(OFF/10%/20%/30%)
Standby Brightness:
Brightness options before light off
Off button means no standby

Time Until Standby
The period before light dims down
to standby brightness after no motion
Press and Hold 30s
for 5 seconds to enter Test Mode

Time Until Standby

30s	1min	3min	10min

Ambient Light Sensor

Off	10lux	30lux	50lux

Daylight threshold
(OFF/10lux/30lux/50lux)

Stand-by Period

5min	15min	30min	+∞

Standby period
(5Min/15Min/30Min/+∞)
Press and Hold 5min
for 5 seconds to enter Test Mode

Note:
The indicator light on the remote will blink
once every time it successfully delivers the
command.