



# BOSCH

## Solution 2000/3000 with the RSC+ App B308 for RSC+ App Output Control

The Bosch Solution 2000/3000 can support 2x B308 Output expansion modules.

Set the Address Switch of the B308 as per below:

First B308:



Second B308:



If you want to use the outputs on B308 for RSC+ app control, please set the **Event Code** for the Outputs to “Remote Control”.

Please use below **Event Code** for RSC+ app control:

- 2 8 = Remote control 1      **Location 646 - 651 (2, 8, 3, 2, 0, 1)**
- 2 9 = Remote control 2      **Location 652 - 657 (2, 9, 3, 2, 0, 1)**
- 2 10 = Remote control 3
- 6 2 = Remote control 4
- 6 3 = Remote control 5
- 6 4 = Remote control 6
- 6 5 = Remote control 7
- 6 6 = Remote control 8

Let's take the first Output on B308 to control the Garage Door as an example.

B308 Output 1		
Item	Location	Data
Event Code	0646	2
Event Code	0647	8
Polarity	0648	3
Time Base	0649	2
Time Base Multiplier	0650	0
Time Base Multiplier	0651	1

You will see “Output 1” on your RSC+ app, then you can click on “Output 1” then Turn on/off your Garage Door.

**Please be aware, if you wish to use Remote Control and App Control to operate 1 door, you will require TWO OUTPUTS from the panel.**

