


# CM720B 1-Amp LAN Power Supply

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ 1 Amp continuous rated; LAN monitored
- ▶ Multiple protected power outputs
- ▶ Resettable fuse protected
- ▶ Pulse battery charger
- ▶ AC Fail output, low battery output and low battery indicator

The CM720B LAN Power Supply is a high efficiency 13.8V DC, 1Amp continuous rated switch mode power supply with built-in Pulse battery charger, suitable for charging up to 7Ah sealed lead batteries. Multiple power outputs are provided to simplify wiring to ancillary equipment and are protected with a self-resetting fuse.

As the CM720 is a LAN device, it can also be mounted in its own enclosure away from the Solution 144 panel, while still remaining fully supervised. A monitored cabinet tamper input is provided for added security when this connection method is used. The CM720 mounts in a single module space within the enclosure.

## Functions

Once connected to the Solution 144 via the RS485 encrypted panel LAN, the Solution 144 panel continuously monitors all functions of the power supply including AC Power Fail, Low Battery, Output Voltage, Overload conditions and even its own temperature. Should any problems be detected, the system will display a trouble message on the code pad, as well as report the event to the monitoring station so they can take appropriate action.

Two fully protected open collector outputs with LED indicators are also provided on board for AC Fail and Low Battery conditions.

## Certifications and approvals

|                       |                                |
|-----------------------|--------------------------------|
| C-tick Supplier Code: | N12138                         |
| CE:                   | EN 55022:2010, EN 60950-1:2001 |
| Telepermit:           | PTC 211/12/017                 |

## Technical specifications

### Power Requirements

|                                      |   |
|--------------------------------------|---|
| Voltage Input (Primary Source):      | 16-18V AC 50-60Hz – 24VA External Power Adaptor or 220-240V AC to 18V AC 50-60Hz – 24VA Internal Transformer    |
| Stand-By Battery (Secondary Source): | 12V DC, 7.2AH sealed rechargeable battery Panasonic LC-P12R2P or equivalent. Resettable Fuse Protected @ 3 Amps |
| Voltage Output:                      | 13.8V DC @ 1 Amp. Ripple 100mV @ Full Load (Primary supply source only)   |

|                     |  |
|---------------------|--|
| Battery Monitoring: | 11.5V DC Low battery trouble at keypads, low battery report sent (if programmed)<br>10.0V DC Shut down as voltage fails below 9V DC<br>13.0V DC Battery trouble clears from keypads, battery restore report sent (if programmed) |
|---------------------|--|

**Connections**

|                                |  |
|--------------------------------|--|
| Module Connection (RS485 LAN): | Max total LAN length using multi strand security cable = 300m<br>Max total LAN length using 2 pair twisted shielded data cable (Belden 8723) = 1200m   |
| Outputs:                       | 3 Output Terminals providing a total of 1 Amp output current (Resettable Fuse Protected)<br>AC Fail – 50mA Max – Sink – 120mA – Overload Protected<br>Low Battery – 50mA Max – Sink – 120mA – Overload Protected |
| Inputs:                        | Cabinet Tamper   |

**Environmental Considerations**

|              |                                  |
|--------------|----------------------------------|
| Temperature: | 0° to 55°C Operating             |
| Humidity:    | 5% to 85% at 30°C non-condensing |

**Enclosure**

|             |                          |
|-------------|--------------------------|
| Dimensions: | 115(W) x 86(D) x 30(H)mm |
| Warranty:   | 3 years                  |

**Ordering information**

**CM720B 1-Amp LAN Power Supply**  
Order number **CM720B**

**Represented by:**

**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**  
Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**  
Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
al.securitysystems@bosch.com  
www.boschsecurity.com