

CONTACT LAYOUT :

Note : Layouts shown are when viewed from the rear of the relay.

	A	B	C	D	
1	+F	+F	+F	+F	
2	-F	-F	-F	-F	
3	+F	+F	+F	+F	
4	-F	-F	-F	-F	
5	-B	+F	+F	-B	
6	+B	-F	-F	+B	
7	-B	+F	+F	-B	
8	+B	-F	-F	+B	
R1	V			V	R2
R3					R4

12F 4B

	A	B	C	D	
1	+F	+F	+F	+F	
2	-F	-F	-F	-F	
3	+F	+F	+F	+F	
4	-F	-F	-F	-F	
5	-B	-B	-B	-B	
6	+B	+B	+B	+B	
7	-B	-B	-B	-B	
8	+B	+B	+B	+B	
R1	V			V	R2
R3					R4

8F 8B

iQN1

- DC neutral
- Line type
- Patent applied for
- SIL4



Product code	Nominal working volt	Contacts	Max full operating volts	Minimum release volts	PIN code
iQN1-12F-4B-50	50	12F 4B	40V	7.5V	ABCEF
iQN1-8F-8B-50	50	8F 8B	40V	7.5V	ABDEF
iQN1-12F-4B-24	24	12F 4B	19.2V	3.6V	ABCDE
iQN1-8F-8B-24	24	8F 8B	19.2V	3.6V	ABCDF
iQN1-12F-4B-12	12	12F 4B	9.6V	1.8V	ACFJX
iQN1-8F-8B-12	12	8F 8B	9.6V	1.8V	ABCFX