

Circuit Breaker Selection Guide, continued

| Circuit Breaker Type | Circuit Breaker Type Code | Continuous Ampere Rating at 40°C | No. of Poles | Volts | | Federal Spec. W-C-375b | UL Listed Interrupting Ratings rms Symmetrical Amperes | | | | | |
|----------------------|---------------------------|----------------------------------|--------------|---------|------------|------------------------|--|---------|--------|------|------|------|
| | | | | AC | DC | | AC Ratings Volts | | | DC ① | | |
| | | | | | | | 120 | 120/240 | 240 | 24 | 48 | 80 |
| QBHGF | B, GF | 15–30 | 1 | 120 | — | 10a, 11a, 12a | 22,000 | — | — | — | — | — |
| QBHGF | B, GF | 15–30 | 2 | 120/240 | — | 10a, 11a, 12a | — | 22,000 | — | — | — | — |
| QBGFEP | B, GFEP | 15–30 | 1 | 120 | — | — | 10,000 | — | — | — | — | — |
| QBGFEP | B, GFEP | 15–50 | 2 | 120/240 | — | — | — | 10,000 | — | — | — | — |
| QBHGFEP | B, GFEP | 15–30 | 1 | 120 | — | — | 22,000 | — | — | — | — | — |
| QBHGFEP | B, GFEP | 15–30 | 2 | 120/240 | — | — | 22,000 | — | — | — | — | — |
| QC | C | 5–70 | 1 | 120/240 | 24, 48, 80 | 10a, 11a, 12a | — | 10,000 | — | 5000 | 5000 | 2000 |
| QC | C | 10–100 | 2 | 120/240 | 24, 48, 80 | 10a, 12a | — | 10,000 | — | 5000 | 5000 | 5000 |
| QC | C | 10–100 | 2, 3 | 240 | — | 10b, 11b, 12b | — | — | 10,000 | — | — | — |
| QC | C | 15–100 | 4 | 240 | — | 10b, 11b, 12b | — | — | 10,000 | — | — | — |
| QCF | C | 10–60 | 1, 2 | 120/240 | — | — | 10,000 | 10,000 | — | — | — | — |
| QCR | C | 10–60 | 1, 2 | 120/240 | — | — | 10,000 | 10,000 | — | — | — | — |
| QCHW | C | 15–70 | 1 | 120/240 | 24, 48, 80 | 14a | — | 22,000 | — | 5000 | 5000 | 2000 |
| QCHW | C | 15–100 | 2 | 120/240 | 24, 48, 80 | 14a | — | 22,000 | — | 5000 | 5000 | 5000 |
| QCHW | C | 15–100 | 2, 3 | 240 | — | 14b | — | — | 22,000 | — | — | — |
| QHCX | C | 15–70 | 1 | 120/240 | 24, 48, 80 | — | — | 42,000 | — | 5000 | 5000 | 2000 |
| QHCX | C | 15–100 | 2 | 120/240 | 24, 48, 80 | — | — | 42,000 | — | 5000 | 5000 | 5000 |
| QHCX | C | 15–100 | 3 | 240 | — | — | — | — | 42,000 | — | — | — |
| QHCW | C | 15–30 | 1 | 120/240 | 24, 48, 80 | 15a | — | 65,000 | — | 5000 | 5000 | 2000 |
| QHCW | C | 15–30 | 2 | 120/240 | 24, 48, 80 | 15a | — | 65,000 | — | 5000 | 5000 | 5000 |
| QHCW | C | 15–30 | 3 | 240 | — | 15b | — | — | 65,000 | — | — | — |
| QCGF | C, GF | 15–30 | 1 | 120 | — | — | 10,000 | — | — | — | — | — |
| QCGF | C, GF | 15–50 | 2 | 120/240 | — | — | 10,000 | 10,000 | — | — | — | — |
| QCHGF | C, GF | 15–30 | 1 | 120 | — | — | 22,000 | — | — | — | — | — |
| QCHGF | C, GF | 15–30 | 2 | 120/240 | — | — | 22,000 | 22,000 | — | — | — | — |
| QCGFEP | C, GFEP | 15–30 | 1 | 120 | — | — | 10,000 | — | — | — | — | — |
| QCGFEP | C, GFEP | 15–30 | 2 | 120/240 | — | — | 10,000 | 10,000 | — | — | — | — |
| QCHGFEP | C, GFEP | 15–30 | 1 | 120 | — | — | 22,000 | — | — | — | — | — |
| QCHGFEP | C, GFEP | 15–30 | 2 | 120/240 | — | — | 22,000 | 22,000 | — | — | — | — |

Notes

① Two-pole DC interrupting rating based on two poles connected in series.

Circuit breaker type codes: **P** Plug-in; **B** Bolt-on; **C** Cable-in/Cable-out; **GF** Ground Fault, 5 mA; **GFEP** Ground Fault, 30 mA.