



## Mi4U

4 channels mixer 2 Microphones, 2 stereo, 1 aux and USB port

---

### Technical data

- Frequency response : 20Hz - 20KHz
- THD @ +10dBu :
- Residual noise
- MAIN output : -103dB
- AUX SEND output : -90dB (only for Mi4U and Mi6U)
  
- Input gain
- Microphone : de 0dB à +45dB
- Line : -20dB à +25dB
  
- Phantom : +48V DC
  
- EQ
- HIGH : +/- 15dB @ 12KHz
- LOW : +/- 15dB @ 80Hz
  
- Max output level
- MAIN/AUX SEND : +21 dBu
- Headphone output : +18 dBu
  
- Input inpedance
- Microphone : 2,3 K Ohms balanced
- Ligne : 20 K Ohms balanced
- Aux / RCA : 24 K Ohms unbalanced
  
- Output inpedance
- MAIN / AUX SEND : 120 Ohms
- REC OUT : 1 K Ohms
- PHONES : 25 Ohms
  
- Vu-meter : -20 dB, -10 dB, 0dB , clip
- Power supply : AC100~240V 50/60 Hz > DC12V 1A switch power adapter
- Power consumption : 11W
- Size (H x L x E) : 220 x 160 x 68 mm
- Weight : 0,78 Kg