






1. Enter Digital Setting

Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p>	<p>If you are unable to enter setting mode after trying step 1, this may be due to an Admin verification is required.</p> <p>You may verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card






2. Add Admin/ User




Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none">1. Face Recognition2. Hand Recognition3. Password4. Fingerprint5. RFID Card	<p>Press on this icon “ User”. You will see the following options:</p> <ol style="list-style-type: none">1. Add User2. Edit User3. Delete User <p>Press on “Add User”, you need to include the Name, Group, Right and ID for the user.</p>
Step 3	
<p>After that, you may register the user using the following option:</p> <ol style="list-style-type: none">1. Face Recognition Scan your face within the box shown on the screen (It will take about 15 seconds to process)2. Hand Recognition Scan your hand within the box shown on the screen (It will take about 15 seconds to process)3. Password Enter 6 pin number and press “Ok” Repeat the step once more.4. Register Fingerprint Scan your preferred fingerprint 3 times to register.5. Setting Up RFID card When prompted to input a new key, tap the RFID Card on the number pad area to complete setup.	



3. Delete Admin/ User




Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card 	<p>Press on this icon “ User”. You will see the following options:</p> <ol style="list-style-type: none"> 1. Add User 2. Edit User 3. Delete User <p>Press on “Delete User”, you may see and choose the User that you would like to delete based on the ID Number E.g. (0002).</p>

4. Setup (Time Setting)




Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card 	<p>Press on this icon “ Setup”. You will see the following options:</p> <ol style="list-style-type: none"> 1. General Setting 2. Super Setting <p>Press on “Gen setting” and press on “Time setting”. You can see the following format:</p> <p>2021 Y 09 M 24 D (Year Month Day)</p> <p>15 H 21 M 38 S (Hour Minute Second)</p>



5. Setup (Volume Setting)




Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card 	<p>Press on this icon “ Setup”. You will see the following options:</p> <ol style="list-style-type: none"> 1. General Setting 2. Super Setting <p>Press on “Gen setting” and press on “Volume setting”. You can see the following options:</p> <ol style="list-style-type: none"> 1. Mute 2. Low 3. Middle 4. High

6. Setup (Language Setting)

Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card 	<p>Press on this icon “ Setup”. You will see the following options:</p> <ol style="list-style-type: none"> 1. General Setting 2. Super Setting <p>Press on “Gen setting” and press on “Language”. You can see the following options:</p> <ol style="list-style-type: none"> 1. 中文 2. English 3. 繁体中文


















7. Setup (Factory Reset)

Step 1	Step 2
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none">1. Face Recognition2. Hand Recognition3. Password4. Fingerprint5. RFID Card	<p>Press on this icon “ Setup”. You will see the following options:</p> <ol style="list-style-type: none">1. General Setting2. Super Setting <p>Press on “Super setting” and press on “Reset”. The system will ask: Factory Reset?</p> <p>Press “OK” and the system will be reset.</p>





8. Setup (Connect to Wi-Fi)(Please download Tuya Smart)





Step 1		Step 2	
<p>Press on “” and then “” to enter setting mode.</p> <p>Verify the system by using the following options:</p> <ol style="list-style-type: none"> 1. Face Recognition 2. Hand Recognition 3. Password 4. Fingerprint 5. RFID Card 		<p>Press on this icon “ Setup”. You will see the following options:</p> <ol style="list-style-type: none"> 1. General Setting 2. Super Setting <p>Press on “Super setting” and press on “Config Wi-Fi”. The system will ask “Start Wi-Fi Config?” Press OK to proceed</p>	
Step 3	Step 4	Step 5	Step 6
<p>Press Sign Up to register for an account</p> 	<p>Please Enter your Email Address</p> 	<p>Press the + button on the top right side</p> 	<p>Press Add Device</p> 

Step 7	Step 8	Step 9	Step 10
<p>Select Security & Video Surveillance on the left side and select Lock (Wi-Fi)</p> 	<p>Enter your home Wi-Fi and password. Press next to proceed. (Ensure it is 2.4 GHz)</p> 	<p>Tick the circle as shown from the picture below. Press next to proceed.</p> 	<p>The app will then proceed to load. It will take about 25-30 second. (Depending on Internet Connection)</p> 
Step 11	Step 12	Step 13	Step 14
<p>The App will show Added Successfully once it has finish loading. Press Done to proceed</p> 	<p>You may press on the lock as shown from the picture below to enter Device</p> 	<p>Once entered, you may see the records as shown from the picture below</p> 	<p>Press on the Green Button to get Remote dynamic password</p> 




Step 15	Step 16	Step 17
<p>You will receive a OTP. Press the 8-digit password on the lock to unlock the door</p>  A screenshot of the SmartLock-6 mobile application. The screen displays a large green oval containing the 8-digit OTP "88264443". Below the oval, it says "Remote dynamic password, invalid after 3 minutes" and "Copy password". The background shows a dark image of a door.	<p>To activate remote unlock, press on The bell button on the lock. You will then see the image as below. Scroll to the right to unlock the gate</p>  A screenshot of the SmartLock-6 mobile application. The screen displays a large green oval containing a white bell icon. Below the oval, it says "Click open remotely". The background shows a dark image of a door.	<p>Press on Confirm to proceed. The door will then be unlocked</p>  A screenshot of the SmartLock-6 mobile application showing a confirmation dialog. The dialog asks "Is this remote opening allowed?" and "Please respond". There are two buttons: "Cancel" and "Confirm". The "Confirm" button is circled in red.

9. Add Member (Tuya Smart)

Step 1	Step 2	Step 3	Step 4
<p>Press on Me at the bottom right corner and then press Home Management</p> 	<p>Press Your House Name to enter Home Setting</p> 	<p>Under Home Setting, ensure that your account name is your email address. Press on Add Member</p> 	<p>Press on App Account</p> 

Step 5

Please enter **Home member name** and His/her **Email Address** under account. Press **Save** to proceed



Cancel **Add Member** Save

Name Please enter a home member name

Region Singapore >

Account Please enter your account

Only after accepting the invitation will the account owner become a family member and be able to use relevant functions.

Family Role Common Member >