



1. Adding Master Password (After Factory Reset Mode)

Step 1	Step 2	Step 3	Step 4
Tap on "*" and then "#" to enter setting mode	Press 1 (New User)	Press 1 (Register key)	Type admin password (6 digits) & press " # "

2. User Manage (Adding Admin or Users)

Step 1	Step 2	Step 3	Step 4
<p>Tap on “*” and then “#” to enter setting mode</p> <p>Verify Admin by passwords or finger vein and press “#”</p>	<p>Press 1 (New User)</p> <p>For add Admin, please enter user number “00” Admin Set</p> <p>For add User, please enter user number from “01” to “99”</p> <p>**NOTE : User 00 is an administrator. The system has no permission to delete the administrator. The administrator can be deleted during initialization</p>	<p>After that press 1 (Register key)</p>	<p>Input information :</p> <ol style="list-style-type: none"> 1. type password and press “#” and repeat again OR 2. scan finger vein 5 times (same position) OR 3. tap the RFID Card on “Card Icon” (below number 5)

3. User Manage (Adding Face ID)

Step 1	Step 2	Step 3	Step 4
<p>Tap on “*” and then “#” to enter setting mode</p> <p>Verify Admin by passwords or finger vein and press “#”</p>	<p>Press 1 (New User)</p> <p>For add Admin, please enter the user number “00” Admin Set</p> <p>For add User, please enter the user number from “01” to “99”</p>	<p>Press 2 (Enrol On Face)</p>	<p>Scan the face 5 times</p>

4. User Manage (Delete Users)

Step 1	Step 2	Step 3
<p>Tap on "*" and then "#" to enter setting mode</p> <p>Verify Admin by passwords or finger vein and press "#"</p>	<p>Press 2 (Delete User)</p>	<p>Please enter the user that you want to delete</p> <p>**NOTE : User 00 is an administrator. The system has no permission to delete the administrator. The administrator can be deleted during initialization</p>

5. System Setting (Time Setting)

Step 1	Step 2	Step 3
<p>Tap on "*" and then "#" to enter setting mode</p> <p>Verify Admin by passwords or finger vein and press "#"</p>	<p>Press 3 (System Setting)</p>	<p>Press 1 (Time Setting) and enter the details in the following format: YYYY : MM : DD HH : MM</p>

6. System Setting (Volume and Language Setting)

Step 1	Step 2	Step 3	Step 4
Tap on "*" and then "#" to enter setting mode Verify Admin by passwords or finger vein and press "#"	Press 3 (System Setting)	Press "2" Volume Setting and you will see the following options: 1. Volume + (press 1 a few times if want to increase volume) 2. Volume - (press 2 a few times if want to decrease volume)	Press 4 (Language Setting) you will see the following options: 1. Chinese 2. English

7. System Setting (Single Mode and Double Mode)

Step 1	Step 2	Step 3	Step 4
Tap on "*" and then "#" to enter setting mode Verify Admin by passwords or finger vein and press "#"	Press 3 (System Setting)	Press "3" verify mode and You will see the following options: 1. Single Mode 2. Double Mode	Press "# " to confirm and Press "*" " to exit setting


8. System Setting (Body Detect/Radar)

Step 1	Step 2
Press 5 and “#” to enter setting mode	After verify You will see the following options: 1. infrared induction on 2. infrared induction off

9. System Setting (Restore Factory Setting/ Factory Reset)

Step 1	Step 2	Step 3	Step 4
Tap on “*” and then “#” to enter setting mode Verify Admin by passwords or finger vein and press “#”	Press 6 (Factory Reset)	Press “#” yes to confirm	Press “*” to exit setting mode

10. Connect to Wi-Fi (Please download USmart Go App)

Step 1	Step 2	Step 3	Step 4
<p>Download USmart Go app into your phone and register for an account first.</p> 	<p>Go to the lock setting Press number “1 and “#” Verify Admin</p>	<p>Go into Usmart Go App and click “Add Device”</p>	<p>Select Connect via Wi-Fi hotspot</p> <p>After that go into your phone’s WiFi Setting and select CloudHome-XXXXXXXXX to connect</p>
Step 5	Step 6	Step 7	Step 8
<p>After connected the CloudHome-XXXXXXXXX WiFi, go back to the Usmart Go App, and it is loading a few seconds</p>	<p>Select your home Wi-Fi to connect and type the password of home Wi-Fi</p> <p>**NOTE: Please connect with 2.4ghz WiFi</p>	<p>Press Search Device and show checking network and wait within 1 minute</p>	<p>Once successful, your phone screen will show “Connected to server” and the system will say success.</p>