

Wireless Home Automation Control Device 3-Way Control Auxiliary Switch with Interchangeable Face Cover



Model No. ZW3K-N

S18831 wall plate sold separately

Description: The ZW3K-N 3-Way Control Auxiliary Switch is a companion device designed to work with the on/off switch ZW15S-N and dimmer switch ZW500D-N. Along the ZW15S-N and ZW500D-N are Single Pole Switches, but the ZW3K-N will enable the 3-way or 4-way switching capability. This auxiliary switch does not need to be connected to the controller, but it must be used with a ZW15S-N or ZW500D-N. Use this ZW3K-N 3-Way Auxiliary Switch to reduce energy consumption and provide more convenience to you and your family.

Operation:

- Once the ZW15S-N or ZW500D-N is configured with the ZW3K-N, the ZW3K-N will mirror all the functions of the ZW15S-N or ZW500D-N. Please refer to the ZW15S-N or ZW500D-N manuals for operating instructions.

Features:

- Perfect replacement for regular light switch, 120VAC, 15Amp.
- Requires a Enerwave home automation switch, not a standalone switch
- Mirrors functionality of the Enerwave smart control lighting switch with which it is paired.
- Manual ON/OFF control of any connected lighting and other electrical load
- 3 Interchangeable Color Face Plates included (white, light almond, and black).
- Ideal use of 3-Ways are in staircases, hallways, and rooms with multiple entrances.

Specifications:

Manufacturer	Enerwave
Included 3 covers	White, Light Almond, and Black
Voltage	120VAC, 60Hz
Work With	ZW15S-N, ZW15SM, ZW500D-N, and ZW500DM
Range	Up to 25 feet in open-air and line of sight distance, depending on obstacles and blocks
Terminations	Neutral, Traveler, and Ground
Operation Temperature	32°F – 104°F (0°C -40 °C), Indoor Use
Warranty	2 years