

## Transformer - 600 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V

Item PX600



### PRODUCT DESCRIPTION

These safety transformers are specifically designed to supply 12-14 VAC and are suitable for direct connection to underwater pool/spa lights. A grounded shield between the primary and secondary winding assures safe operation. Built-in circuit protection will disconnect power to the transformer in case of an overload.

### FEATURES

- ▶ Mounting brackets on the top and bottom
- ▶ Built-in circuit protection disconnects power temporarily in case of overload
- ▶ Complies with NEC Code 680.23 requirements for underwater luminaires

### APPLICATIONS

- ▶ Landscape Lighting
- ▶ Underwater Lighting

### TECHNICAL DATA

#### General

Model Number	PX600
Description	600 W Pool & Spa Safety Transformer, Beige Steel Enclosure, Input 120V, Output 12,13,14V
UPC Code	078275079854
Brand	Intermatic
Country of Origin (Intermatic)	MEXICO
Warranty Period	1-Year limited

#### Mechanical Specifications

Enclosure Type	3R Beige metal
----------------	----------------

#### Dimensions

Product Dimensions (H x W x D) in	10 x 10 x 5.375 in
Knockout Dimensions Bottom	(2) combination 1/2" - 3/4", (4) combination 3/4" - 1"
Knockout Dimensions Back	(2) combination 1/2" - 3/4"
Knockout Dimensions Left	(2) combination 1/2" - 3/4"
Knockout Dimensions Right	(2) combination 1/2" - 3/4"

#### Electrical Specifications

Output Voltages	12 VAC; 13 VAC; 14 VAC
Maximum Power Consumption (W)	600 W
Transformer (W)	600
Transformer Input Voltage	6 A, 120 VAC, 60 Hz
Transformer Output Voltage	12, 13, 14 VAC

#### Packaging

Unit Carton Dimensions (H x W x L) in	11.751 x 6.001 x 10.751 in
---------------------------------------	----------------------------

#### Standards and Certifications

CSA Certification	cCSAus
Other Certifications and Compatibilities	NEC Code 680.23
California Proposition 65	DEHP

---

## ACCESSORIES



ET-NF  
RC Snubber Noise Filter 24-277VAC/DC for Electronic Controls