

Load Center - 100 A Load Center Only with 300 W Transformer, 8-Breaker Spaces

Item T40000RT3



PRODUCT DESCRIPTION

These mechanical control systems include built-in transformers for ease of installation.

FEATURES

- Load Centers have eight breaker spaces
- ► All-in-one control power for pool/spa installation
- Easy to wire
- > Can house additional Intermatic mechanisms and components
- Control two-speed pumps with the T40604RT3
- ► Heavy-duty Type 3R metal indoor/outdoor power and load center
- > Wiring devices may be installed in these Load Centers with the use of Standoffs, sold separately
- Knockout on the side for additional wiring device

APPLICATIONS

- Distribution/Control Panel
- Motor Control
- Pump Control

TECHNICAL DATA

General	
Model Number	T40000RT3
Description	100 A Load Center Only with 300 W Transformer, 8-Breaker Spaces
UPC Code	078275125605
Brand	Intermatic
Country of Origin (Intermatic)	MEXICO
Warranty Period	1-Year limited
Mechanical Specifications	
Number of Breaker Knockouts	8
Dimensions	
Product Dimensions (H x W x D) in	20.875 x 12.875 x 4.75 in
Knockout Dimensions Bottom	(5) 7/8" - 1 7/8", (4) 7/8", (2) 1 1/8" - 1 3/8" - 1 5/8"
Knockout Dimensions Back	(4) 7/8" - 1 1/8", (2) 1 1/8" - 1 3/8"
Knockout Dimensions Left	(2) 7/8" - 1 1/8"
Knockout Dimensions Right	(1) 1 3/4" x 2 3/4"
Electrical Specifications	
Number of Receptacle Knockouts	1
Packaging	
Unit Carton Dimensions (H x W x L) in	6 x 14 x 22 in
Standards and Certifications	
CSA Certification	cCSAus

California Proposition 65

None





ACCESSORIES



156T1978AMX 1 Set of ON/OFF Trippers for T100, T7000, and WH40



156T1978A Extra/replacement trippers 1 ON and 1 OFF



124--00066 Insulator for 3-Circuit Timers



21T166A Spacer-Standoff, 3" long - 2 pack



Spacer-Standoff, 3" long - 4 pack

21T156A

ET-10 HET IN BELL BELL HET IN BELL HET IN

ET-NF RC Snubber Noise Filter 24-277VAC/DC for Electronic Controls



22T338GR Mounting Bracket for Intermatic Standardized Timer Mechanisms