

Racing Radios Helmet Kit Installation

Included in kit: Helmet Cord, Earpiece Jack, Microphone

Installation hardware: Earpiece Jack Velcro Mounting Tab, Heat Shrink x4, Zip Tie x2

Additional Tools Needed for Install :

- Hot Glue Gun
- *Heat Gun or Hair Dryer, or Lighter*

Step 1.

Pull back cheek pad on the side you are mounting equipment.

Step 2.

Secure **Earpiece Jack** with **Velcro Mount Tab**

Step 3.

Connect **Helmet Cord** and **Earpiece Jack** together

- On the Helmet Cord:
Slide one heat shrink over the green wire
Slide one heat shrink over the white wire
(to use later once wire is connected)
- Connect Helmet Cord **Green wire** to Earpiece Jack **Blue wire**
- Connect Helmet Cord **White wire** to Earpiece Jack **Black wire**
- Slide heat shrink over connection & apply heat to shrink

Step 4.

Secure Helmet wire and Earpiece wire together with zip ties.

Step 5.

Depending on style of helmet

Cut hole in cheek pad and feed microphone through to the backside of the cheek pad

Channel out groove on the backside of the cheek pad and secure mic with hot glue

Let it dry for about 5 minutes.

Step 6.

After glue is dry, connect 2 microphone wires to the two remaining wires on the Helmet Cord. It does not matter which color goes to what wire.

Secure these connections with heat shrink also.

Step 7.

- Secure cheek pad back into helmet and make sure everything is fitting correctly.
- Test Helmet and make sure everything is functioning properly.