



<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>WV-6038-LI</b>

COMPATIBLE RADIOS	Motorola APX 6000, APX 6000XE, APX 7000, APX 7000XE, APX 8000, APX8000XE, SRX 2200
REPLACES OEM BATTERY	PMNN4486
COMPATIBLE CHARGERS	Endura EC1-MT19B, EC1M-MT19B, EC6M-MT19B, EC2M-MT19B-D, EC12M-MT19B-D / Logic LEVCA-MT19 / Motorola adaptive IMPRES 1 and 2 chargers
VOLTAGE	7.4V
CAPACITY	3400 mAh / 25.2 Wh
CHEMISTRY	Lithium Ion
CELL TYPE	Panasonic Japanese
OPERATING TEMPERATURE	-10° C to +50° C (discharge) / 0° C to +45° C (charge)
CHARGE CYCLES	>500
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Smart battery conditions on Motorola IMPRES chargers (conditioning not required for cycle life or battery run time)
PROTECTION TYPES	Over-charge / over-discharge / over-temperature
HOUSING MATERIAL / SEAL	ABS / ultrasonic weld
INGRESS PROTECTION	IP68 rated
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	24 months (capacity 80%) 24 months (materials and workmanship)