

- Split polyurethane housing allows easy access without having to remove the
- Easy to adjust electronic magnetic limits eliminate old style mechanical switches



simple manual release



steel frame for strength and durability



breakaway hub prevents gearbox damage




easily adjustable electronic magnetic limits

# 6500 VEHICULAR SMING GATE OPERATOR



18.375" W x 31.625" H x 23.25" D (466.7 mm W x 803.3 mm H x 590.5 mm D)



	CLASS OF OPERATION	MAX GATE LENGTH *	MAX GATE WEIGHT *	MOTOR	INPUT	OPTIONS
6500 1/2 HP	I, II, III, IV	18 Ft (5.5 m)	700 Lbs. (317.5 kg)	1/2HP Continuous Duty AC Motor	115 VAC, 60 HZ, 5.4A 208 VAC, 60 Hz, 2.8A** 230 VAC, 60 Hz, 2.7A** 460 VAC, 60 Hz, 1.4A**	Convenience Open Package † Heater Kit Uphill Arm Pivot Kit
6500 1 HP	I, II, III, IV	22 Ft (6.7 m)	800 Lbs. (362.8 kg)	1HP Continuous Duty AC Motor	115 VAC, 60 HZ, 9.7A 208 VAC, 60 Hz, 5.0A ** 230 VAC, 60 Hz, 4.9A ** 460 VAC, 60 Hz, 2.5A**	Convenience Open Package † Heater Kit Uphill Arm Pivot Kit

<sup>\*</sup> Assumes gate to be in good condition and swinging in a level plane. When combined with convenience open option, 1/2HP max weight is 600 Lbs., 1 HP max weight is 700 Lbs.

# **Technical Features**

## **Mechanical**

Primary Reduction is provided by a pulley / belt driving a 60:1 worm gear reduction system running in a continuous oil bath

The 6500 rotates the gate 90° in approximately 12-14 seconds

Operator mechanics are mounted on a steel frame plated for corrosion resistance

Two-piece articulating arm mechanical slow start / slow stop function.

Mounting: Operator is mounted to a concrete mounting pad

Keyed access is provided to release arm for manual gate operation in the event of a power outage

Split polyurethane housing simplifies installation and maintenance. No need to remove the gate arm

Unique breakaway hub helps to protect the gear box if the gate is rammed

## **Electrical**

Adjustable electronic magnetic limits

Auto-close timer (1-23 seconds)

Gate overlap feature for bi-parting (dual) gate operation

Simple connection for secondary operator in bi-parting gate systems

Built-in On / Off switch

Built-in alarm reset switch

Selectable shadow / reverse loop function

Magnetic lock power

Ports for plug-in open and reverse loop detectors. DKS plug-in detectors only

Three 115 VAC convenience outlets for accessory transformers

Gate Tracker reporting output provides operator data to access control system (DKS 1833, 1835, 1837 or 1838 only)

## **Miscellaneous**

Environmental: 10°F to 115°F (-12°C to 46°C)

Thermostatically controlled heater kit recommended for colder environments

Shipping weight approximately 175-225 Lbs (79.1-101.8~kg) Depending on model and options selected

External entrapment/ obstruction sensing devices must be used with this operator





Access Control Solutions since 1948

Distributed by:

















### DOORKING, INC.

120 Glasgow Avenue, Inglewood, California 90301 U.S.A. Tel: 310-645-0023 FAX: 310-641-1586 www.doorking.com

© 2013 All Rights Reserved. Product specifications may change without notice. Rev. 9/13

<sup>\*\*</sup> These operators use a step-down transformer to achieve 115 VAC operating voltage.

<sup>†</sup> Optional factory installed DC powered drive system provides an automatic method to open the gate when primary (AC) power fails.