

# **Wireless Video Door Phone**

#### DP-266-1C7Q

The ENFORCER Wireless Video Door Phone is a stand-alone, home entry solution. Observe visitors on the large 7" screen as they arrive, communicate with them, take photos or videos for later viewing, and unlock a gate to grant entry – all from the wireless monitor. Connect up to 3 monitors with 2 cameras for viewing multiple entrances around the house.





#### **Features**

- Talk with visitors and unlock doors or gates via the monitor
- Monitor's rechargeable battery allows convenient communication with visitors while moving around the premises
- Connect up to 2 additional monitors and 1 additional camera (sold separately)
- · Intercom calling between paired monitors
- Egress input allows the door phone to be connected to a Request to Exit Plate or other egress device
- Camera has a 170° field of view with adjustable pan and tilt angle to accommodate a variety of installations
- Camera has built-in IR LEDs for nighttime operation
- Camera's built-in PIR sensor activates camera to take photos or record video of approaching visitors
- Tamper switch triggers alarm if camera is removed from base



Built-in Kickstand for Wall or Table Mount



#### **Wireless Operation**

Range: Up to 492ft (150m)\*



#### **Unlocks Doors**

Allows access remotely via the monitor



#### 2 Cameras, 3 Monitors

Pair up to 3 monitors with 2 cameras













SECO-LARM® U.S.A., Inc.


16842 Millikan Avenue, Irvine, CA 92606

**Phone:** (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com





#### **Overview**

#### Camera





Front






**Monitor** 







### **On-Screen Display Features**



Photos – View and delete photos taken by the camera station.



Time - Set the time and date.



**Video** – View and delete videos taken by the camera station.



Messages - View photos from missed calls.



**Ring** – Choose from four different ring tones and set ring volume (six levels).



**Setup** – Set advanced settings such as motion detection, backlight time, unlocking duration, pairing, or alarm settings.

### **Specifications**

Camera			
Туре		Color camera	
Chip		CMOS	
Resolution		640 TV lines	
Lens		2mm	
Field of view		170°	
Camera angle adjustment		Up to 20° any direction	
Operating voltage		9~16 VAC / 5~16 VDC	
Relock delay		3/6/8 Seconds	
Relay output		3A@24VAC/24VDC	
Current draw	Active	300mA@12VDC	
	Standby	15mA@12VDC	
Battery life	Active	~7 hours	
	Standby	~60 Days	
IR LED range		5' (1.5m)	
IR LED frequency		940nm	
PIR detection range		9' (3m)	
Operating temperature		14°~122° F (-10°~50° C)	
Dimensions		5 <sup>11</sup> / <sub>16</sub> "x3 <sup>1</sup> / <sub>8</sub> "x1 <sup>15</sup> / <sub>16</sub> " (144x80x50 mm)	
Weight		4.3-oz (122g)	

Monitor			
Display		7" (178mm) TFT	
Operating voltage		12VDC (adapter) or 3.7VDC (battery)	
Current draw	Active	600mA@3.7VDC	
	Standby	5mA@3.7VDC	
Battery life	Active	~2.5 hours	
	Standby	~7 days	
Antenna gain		0dBi	
Modulation type		GFSK	
Operating frequency		2402~2480MHz	
RF Power		120mW	
Wireless range		492 (150m)*	
Operating temperature		32°~95° F (-5°~35° C)	
Dimensions		8" x 6" x 1 <sup>1</sup> / <sub>8</sub> " (203 x 153 x 27mm)	
Weight		1.2-lb (544g)	

<sup>\*</sup> Line-of-sight range. Actual range may vary depending on the installation and operating environment

## **Sample Wiring Diagram**

